

Two-Scale Approach to an Asymptotic Solution of Maxwell Equations in Layered Periodic Medium

M. V. Perel^{1, a)} and M. S. Sidorenko^{1, b)}

St. Petersburg State University, 7/9 Universitetskaya nab., St. Petersburg 199034, Russia.

(Dated: 10 May 2016)

An asymptotic investigation of monochromatic electromagnetic fields in a layered periodic medium is carried out in the assumption that the wave frequency is close to the frequency of a stationary point of a dispersion surface. We find solutions of Maxwell equations by the method of two-scale asymptotic expansions. We establish that the principal order of the expansion of a solution dependent on three spatial coordinates is the sum of two differently polarized Floquet-Bloch solutions, each of which is multiplied by a slowly varying envelope function. We derive that the envelope functions satisfy a system of differential equations with constant coefficients. In new variables, it is reduced to a system of two independent equations, both of them are either hyperbolic or elliptic, depending on the type of the stationary point. The envelope functions are independent only in the planar case. Some consequences are discussed.

^{a)}Electronic mail: m.perel@spbu.ru

^{b)}Electronic mail: m-sidorenko@yandex.ru

I. INTRODUCTION

The propagation of electromagnetic waves in media with periodic changes of dielectric permittivity and magnetic permeability, in the so-called photonic crystals, is a subject of many investigations (see, for example,¹). The popularity of such studies is caused, on the one hand, by unusual properties of such media, which are yet not completely known and which promise new applications. On the other hand, there is a technological progress in the creation of artificial structures with prescribed properties.

The problem of wave propagation in a quickly oscillating medium can be usually reduced to a problem of wave propagation in an effective homogeneous medium. The mathematic methods applied in finding the effective medium are methods of homogenization^{2,3,4}, i.e., asymptotic methods in the long wavelength approximation: $kb \rightarrow \infty$, where k is the wavenumber, b is the period of oscillations of the medium. One of the methods of the derivation of asymptotic formulas is the method of two-scale expansions. The solution is assumed to depend on fast and slow distance variables. It turns out that the principal term is a function of only a slow variable and satisfies homogenized equations, which may be interpreted as equations in an effective medium. Another approach is based on the spectral point of view: the field can be represented as a superposition of Floquet-Bloch solutions corresponding to the lower part of the spectrum.

A lot of physical works use the concept of effective medium. Peculiarities of a dispersive surface in an effective medium are responsible for unusual phenomena of wave propagation in such structures, which are often not observed in nature. For example, if one of the principal components of the effective electric or magnetic tensor has an opposite sign with respect to other two principal components, the dispersive surface in such a medium has a hyperbolic point. Such media are named hyperbolic ones and are studied intensively; see, for example,⁵. Another example is a composite material consisting of layers of metals and dielectrics. The isofrequency dispersive surface for such a structure may have a plane part, i.e., one of the components of the wavevector may be almost independent of the other two. The waves may propagate without distortion in such a medium, see⁶.

The present work was motivated by papers of Longhi^{7,8}, in which the possibilities of the existence of localized waves in 2D and 3D periodic structures were studied. The idea was to take the frequency of a monochromatic electromagnetic field equal to the frequency of

the stationary point of the dispersive (band) surface in the periodic structure. The field in 2D and 3D photonic crystals was represented as a superposition of Wannier functions with an envelope, which satisfies the equation with constant coefficients. For hyperbolic (saddle) point the envelope satisfies the wave equation, where one of the spatial coordinates stands for time. By choosing for the envelope one of the known solutions of the wave equation with finite energy, see, for example,⁹, one may obtain localized waves in the periodic structure. The papers^{7,8} were mainly concentrated on physical aspects of the problem. We are more interested in careful mathematical analysis and obtain new results in the 3D case.

We noted in our paper¹⁰ that the local hyperbolic behavior of a dispersive surface occurs even for the simplest dielectric layered periodic structures, for example, for a structure with alternating layers of dielectric. In this case we studied a field dependent only on two spatial coordinates in¹⁰ and found and numerically confirmed the following physical phenomenon: undistorted beams can propagate in such a structure and there are only two permitted directions of a beam in the medium, which differs by a sign from the angle with the normal to layers. A similar phenomenon was found before by numerical simulation in 2D crystals in¹¹; but it was not investigated analytically.

In the present paper, we study monochromatic electromagnetic fields with a frequency close to that of a stationary point of the dispersive surface, which may be a hyperbolic or an elliptic one. The field is studied in a layered structure with periodically varying dielectric permittivity and the magnetic permeability. We deal with fields dependent on all the three spatial coordinates. Our aim is to elaborate a mathematical asymptotic approach for the description of solutions of Maxwell equations.

The two-scale method in the homogenization theory is applied usually to equations written in divergent form. Our asymptotic scheme is applied to Maxwell equations in matrix form, which was first suggested in the book by Felsen and Marcuvitz¹². This form was also used in the turning points problem for the Maxwell equations in¹³, for other particular equations in^{14,15,16}, and for the operators in the general form¹⁷. Therefore we believe that results may have generalizations to other problems. The matrix form of the Maxwell equations is given in Section III.

In Section IV we discuss difficulties in studying electromagnetic fields dependent on three spatial variables caused by the fact that the stationary points are common for waves of both the TM and the TE polarizations, and that the concepts of TM and TE polarizations depend

on the direction of propagation and at the stationary point itself they lose their meaning. In Section V, we obtain some integral formulas for second derivatives of the dispersion functions, which are applied in the next section. In Section VI, we develop the two-scale expansions method for our problem. Apart from the period b in z direction we introduce the second scale of length, which is a scale of field variation in the (x, y) plane denoted by L . We regard the ratio between b and L as a small parameter χ . We consider the entire formal asymptotic series and show that the recurrent system for subsequent approximations can be solved step by step. In Section VI, we found that the principal term of the two-scaled field is obtained as a sum of two differently polarized Floquet-Bloch solutions at the stationary point and each of these solutions has a slowly varying envelope function. The envelope functions satisfy a system of two partial differential equations with constant coefficients. In Section VII, we show that these equations are independent only if the envelopes depend on two spatial coordinates. A qualitative consequence of equations is that undistorted beams can propagate in the medium. In the general 3D case, each envelope function can be expressed in terms of two functions. These functions are solutions of two equations, which are of the Helmholtz type or the Klein-Gordon-Fock type for elliptic or hyperbolic stationary points, respectively. The fact that the wave field is described by a system of two equations was not predicted in the papers^{7,8}. Our paper is concluded with two Appendices. Appendix 1 contains known results important for the present paper from the Floquet-Bloch theory, which are given in our notation. Appendix 2 contains proofs of two lemmas.

Our case may be regarded as homogenization near a stationary point of the dispersive surface in contrast to a more usual situation, where the frequency corresponds to the lower part of the spectrum and obtained in the assumption that $kb \rightarrow 0$. Our case demands an assumption $kb \sim 1/\sqrt{\varepsilon_{av}\mu_{av}}$, where ε_{av} , μ_{av} are typical permittivity and permeability. The equations for envelopes are analogous to equations in an effective medium and can be used for a qualitative description of the wavefield.

II. STATEMENT OF THE PROBLEM

A monochromatic electromagnetic field satisfies the Maxwell equations

$$\begin{aligned}\operatorname{rot}\mathbb{E} &= ik\mu\mathbb{H}, \\ \operatorname{rot}\mathbb{H} &= -ik\varepsilon\mathbb{E},\end{aligned}\tag{1}$$

where $\varepsilon(z+b) = \varepsilon(z)$, $\mu(z+b) = \mu(z)$; ε and μ are piecewise continuous.

The medium with alternating dielectric layers is a practically important special case.

We seek solutions under two assumptions. The first assumption is about the parameters of the problem. The Maxwell equations contain two parameters of length dimension: the wavelength $\lambda = 2\pi/k$ and the period of the medium b . We introduce the third parameter of length dimension L , which is the scale of variation of the field in the (x, y) plane. We assume that the parameter $\chi \equiv b/L$ is small:

$$\chi = b/L \ll 1. \quad (2)$$

The second assumption is related to the frequency of the monochromatic field ω . To state this assumption, we need some concepts: the quasimomentum $\mathbf{p}$, the dispersive surface $\omega = \omega(\mathbf{p})$, and Floquet-Bloch solutions. We determine and discuss in detail all these concepts in Appendix 1. This assumption means that the frequency ω is close to that of the stationary point of the dispersive surface ω_* :

$$\omega = \omega_* + \chi^2 \delta\omega, \quad \delta\omega \sim 1, \quad (3)$$

where ω_* satisfies the condition

$$\nabla\omega|_{\mathbf{p}_*} = 0, \quad \omega_* = \omega(\mathbf{p}_*). \quad (4)$$

We shall see that these stationary points are minima and saddle points. There is also an additional condition, which we shall introduce later.

III. MATRIX FORM OF MAXWELL EQUATIONS

We represent the Maxwell equations in matrix form for the sake of brevity and generality of subsequent asymptotic considerations:

$$kP\Psi = -i\hat{\Gamma} \cdot \nabla\Psi, \quad \Psi = \begin{pmatrix} \mathbb{E} \\ \mathbb{H} \end{pmatrix}, \quad (5)$$

$$\hat{\Gamma} \cdot \nabla \equiv \Gamma_1 \frac{\partial}{\partial x} + \Gamma_2 \frac{\partial}{\partial y} + \Gamma_3 \frac{\partial}{\partial z}, \quad (6)$$

where

$$\mathbf{P} = \begin{pmatrix} \varepsilon I & 0 \\ 0 & \mu I \end{pmatrix}, \quad \Gamma_1 = \begin{pmatrix} 0 & \gamma_1 \\ -\gamma_1 & 0 \end{pmatrix}, \quad \Gamma_2 = -\begin{pmatrix} 0 & \gamma_2 \\ -\gamma_2 & 0 \end{pmatrix}, \quad \Gamma_3 = \begin{pmatrix} 0 & \gamma_3 \\ -\gamma_3 & 0 \end{pmatrix},$$

$$\gamma_1 = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & -1 & 0 \end{pmatrix}, \quad \gamma_2 = \begin{pmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ -1 & 0 & 0 \end{pmatrix}, \quad \gamma_3 = \begin{pmatrix} 0 & 1 & 0 \\ -1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad (7)$$

and $k/\sqrt{\varepsilon_{av}\mu_{av}} = \omega/c$, where c is the speed of light in vacuum.

We introduce two types of inner products. Let $\mathbf{v}(z)$ and $\mathbf{w}(z)$ be 6-component complex-valued vector functions; then

$$\langle \mathbf{v}, \mathbf{w} \rangle = \sum_{j=1}^6 \overline{v^j} w^j, \quad j = 1, \dots, 6, \quad (8)$$

where the bar over the symbol stands for complex conjugation. If $\mathbf{v}$ and $\mathbf{w}$ are periodic with period b and piecewise continuous, we define $(\mathbf{v}, \mathbf{w})$ as follows:

$$(\mathbf{v}, \mathbf{w}) = \int_0^b \langle \mathbf{v}(z), \mathbf{w}(z) \rangle dz. \quad (9)$$

The Umov-Poynting vector, averaged over time, for a monochromatic field of frequency ω , i.e., the energy flux density of this field, averaged over $T = 2\pi/\omega$, is determined as

$$\mathbf{s} = \frac{1}{2} \text{Re} \overline{\mathbb{E}} \times \mathbb{H}. \quad (10)$$

It is easy to check that

$$\langle \Psi, \Gamma_j \Psi \rangle = 4s_j, \quad j = 1, 2, 3; \quad (\Psi, \Gamma_j \Psi) = 2 \int_0^b \text{Re} [\overline{\mathbb{E}} \times \mathbb{H}]_j dz. \quad (11)$$

The density of electromagnetic energy, averaged over time, in the case of real ε and μ reads

$$u = \frac{\varepsilon}{4} |\mathbb{E}|^2 + \frac{\mu}{4} |\mathbb{H}|^2. \quad (12)$$

We note that

$$\langle \Psi, \mathbf{P} \Psi \rangle = 4u, \quad (\Psi, \mathbf{P} \Psi) = \int_0^b (\varepsilon |\mathbb{E}|^2 + \mu |\mathbb{H}|^2) dz. \quad (13)$$

IV. THE FLOQUET-BLOCH SOLUTIONS AND THE DISPERSION RELATION

Since the properties of the medium do not depend on x, y , we shall seek particular solutions in the form

$$\Psi_B(x, y, z; \mathbf{p}) = e^{i(p_x x + p_y y)} \Phi(z; \mathbf{p}), \quad \Phi = \begin{pmatrix} \mathbf{E} \\ \mathbf{H} \end{pmatrix}, \quad (14)$$

where the parameters p_x and p_y are lateral components of the wave vector. The components of the vector-valued function $\Phi(z; \mathbf{p})$ satisfy a system of ordinary differential equations with periodic coefficients:

$$k\mathbf{P}\Phi + i\Gamma_3 \frac{\partial \Phi}{\partial z} = p_x \Gamma_1 \Phi + p_y \Gamma_2 \Phi. \quad (15)$$

We are going to obtain Floquet-Bloch solutions of this system. However there are difficulties owing to the vector nature of the problem. It is well known (see, for example,¹²) that an appropriate choice of the coordinate system allows one to split the system (15) into two independent subsystems. These subsystems describe waves of two polarizations: the transverse electric wave and the transverse magnetic waves, which are named the TE and TM waves, respectively. We call the coordinates, in which such a splitting occurs, the natural ones.

A. Two types of Floquet-Bloch solutions in the natural coordinates

To determine the type of a solution, we should clarify, which component of the wave is transverse to the propagation plane, the electric or the magnetic one. The propagation plane passes through the lateral wave vector (p_x, p_y) and the z axis. To find the TM and TE modes, it is convenient to rotate the axes in the (x, y) plane through an angle γ , so that in the new coordinates, $\tilde{p}_y = 0$, $\tilde{p}_x \equiv p_{\parallel} = \sqrt{p_x^2 + p_y^2}$. We denote fields in the rotated coordinate system by a tilde. The waves of TE and TM types are as follows:

$$\tilde{\Phi}^E = \left(0, E_{\perp}, 0, H_{\parallel}, 0, \frac{p_{\parallel}}{k\mu} E_{\perp} \right)^t, \quad \tilde{\Phi}^H = \left(E_{\parallel}, 0, -\frac{p_{\parallel}}{k\varepsilon} H_{\perp}, 0, H_{\perp}, 0 \right)^t. \quad (16)$$

The system of equations (15) in such coordinates splits into two subsystems:

$$\begin{cases} i \frac{\partial H_{\perp}}{\partial z} = -k\varepsilon E_{\parallel}, \\ i \frac{\partial E_{\parallel}}{\partial z} = -\left(\frac{k^2 \varepsilon \mu - p_{\parallel}^2}{k\varepsilon} \right) H_{\perp}. \end{cases}, \quad \begin{cases} i \frac{\partial H_{\parallel}}{\partial z} = \left(\frac{k^2 \varepsilon \mu - p_{\parallel}^2}{k\mu} \right) E_{\perp}, \\ i \frac{\partial E_{\perp}}{\partial z} = k\mu H_{\parallel}. \end{cases} \quad (17)$$

In the special case $p_{\parallel} = 0$, the splitting into TM and TE waves has no meaning: both systems can be reduced to the following one:

$$i \frac{dE_0}{dz} = -k\mu H_0; \quad i \frac{dH_0}{dz} = -k\varepsilon E_0, \quad (18)$$

where

$$E_{\parallel}|_{p_{\parallel}=0} = E_0, \quad H_{\perp}|_{p_{\parallel}=0} = H_0, \quad E_{\perp}|_{p_{\parallel}=0} = -E_0, \quad H_{\parallel}|_{p_{\parallel}=0} = H_0. \quad (19)$$

We introduce the new notation for vector-functions obtained by means of the passage to the limit $p_{\parallel} \rightarrow 0$ in $\tilde{\Phi}^E, \tilde{\Phi}^H$:

$$\tilde{\Phi}^E|_{p_{\parallel} \rightarrow 0} \rightarrow \Phi^X, \quad \tilde{\Phi}^H|_{p_{\parallel} \rightarrow 0} \rightarrow \Phi^Y, \quad (20)$$

where

$$\Phi^X = (E_0, 0, 0, 0, H_0, 0)^t, \quad \Phi^Y = (0, -E_0, 0, H_0, 0, 0)^t. \quad (21)$$

The superscript X (or Y) indicates that the vector-function has the nonzero first (or second) component.

The obtained systems of ordinary linear differential equations (17), (18) for $E_{\parallel}, H_{\perp}$ and $E_{\perp}, H_{\parallel}$ and for E_0 and H_0 , respectively, are systems with piecewise continuous periodic coefficients, because ε and μ are piecewise continuous. Each system has two Floquet-Bloch solutions; for details, see Appendix 1. We denote the components of the second solution by the subscript 2. For example, the two solutions of the first subsystem of (17) for TM waves read

$$\begin{pmatrix} E_{\parallel} \\ H_{\perp} \end{pmatrix} = e^{ip_z z} \mathbf{U}_+^H(z; p_z, p_{\parallel}^2, \omega), \quad \begin{pmatrix} E_{\parallel 2} \\ H_{\perp 2} \end{pmatrix} = e^{-ip_z z} \mathbf{U}_-^H(z; p_z, p_{\parallel}^2, \omega). \quad (22)$$

The solutions depend on the parameters of the equations $p_{\parallel}^2$ and ω , and also on the real-valued parameter p_z , which is called the quasimomentum and which is related to $p_{\parallel}^2$ and ω by the formula

$$p_z = p_z(p_{\parallel}^2, \omega). \quad (23)$$

This relation ensures that the functions $\mathbf{U}_{\pm}^H$ are periodic,

$$\mathbf{U}_{\pm}^H(z + b; p_z, p_{\parallel}^2, \omega) = \mathbf{U}_{\pm}^H(z; p_z, p_{\parallel}^2, \omega), \quad (24)$$

and continuous as functions of the z variable. We call these functions *Floquet-Bloch amplitudes*. The relation (23) can be reduced to the following one:

$$\omega = \omega^H(\mathbf{p}). \quad (25)$$

We call this equation the *dispersion relation*. The function $\omega^H(\mathbf{p})$ is called the *dispersion function*. It is a multisheeted function on $[-\pi/b, \pi/b] \times \mathbb{R}_+^2$, and its derivation is discussed in

the Appendix 1. Substituting (25) into (22), we obtain $E_{\parallel}$ and $H_{\perp}$ as functions of z and $\mathbf{p}$. The Floquet-Bloch solutions and the dispersion function for the waves of TE type ($E_{\perp}$, $H_{\parallel}$) and for the solutions E_0 and H_0 of the system (18) are obtained analogously. The solutions (22) are linearly independent if $p_z \neq 0, \pm\pi/b$; see Appendix 1. However, this particular case $p_z = 0, \pm\pi/b$ is important in the present paper.

We are interested here in effects that arise if the frequency of the problem is close to the frequency of one of the stationary points of some sheet of the dispersive surface. In Appendix 1, we show that the multisheeted dispersive surfaces $\omega = \omega^H(\mathbf{p})$ and $\omega = \omega^E(\mathbf{p})$ have stationary points on each sheet, at the points $\mathbf{p}_*$, $p_{\parallel*} = 0$, $p_{z*} = 0, \pm\pi/b$, where $\nabla\omega_{\mathbf{p}_*}^E = 0$. In these points the sheets of the dispersive surfaces for TM and TE polarizations touch each other, and therefore $\nabla\omega_{\mathbf{p}_*}^H = \nabla\omega_{\mathbf{p}_*}^E = 0$ and $\omega^E(\mathbf{p}_*) = \omega^H(\mathbf{p}_*) \equiv \omega_*$. At the point $\mathbf{p}_*$, formulas (22) may give the same solution, which is bounded at infinity and which is periodic for $p_{z*} = 0$ and anti-periodic for $p_{z*} = \pm\pi/b$. Then the second solution, which is linearly independent with the first one, grows at infinity (for details, see Appendix 1). It is this case that is of interest to us in the present paper. The solutions read

$$\begin{aligned} \left(\begin{array}{c} E_{\parallel} \\ H_{\perp} \end{array} \right) \Big|_{\mathbf{p}=\mathbf{p}_*} &= \left(\begin{array}{c} E_0 \\ H_0 \end{array} \right) \Big|_{p_z=p_{z*}} = e^{ip_{z*}z} \mathbf{U}_+^H(z; p_{z*}, 0, \omega_*), \\ \left(\begin{array}{c} E_{\parallel 2} \\ H_{\perp 2} \end{array} \right) \Big|_{\mathbf{p}=\mathbf{p}_*} &= \left(\begin{array}{c} E_{02} \\ H_{02} \end{array} \right) \Big|_{p_z=p_{z*}} = e^{ip_{z*}z} \left[e^{-ip_{z*}b} \frac{z}{b} \mathbf{U}_+^H(z; p_{z*}, 0, \omega_*) + \mathbf{Q}^H(z; p_{z*}, \omega_*) \right], \end{aligned} \quad (26)$$

where the vector-valued function $\mathbf{Q}^H$ is a periodic and continuous function of the variable z . The function $\mathbf{Q}^H$ does not depend on the argument $p_{\parallel*}^2$, because $p_{\parallel*}^2 = 0$, and we are not going to use the second solution (26) for $p_{\parallel} \neq 0$.

The solutions of the second subsystem (17) are expressed in the following way:

$$\left(\begin{array}{c} E_{\perp} \\ H_{\parallel} \end{array} \right) \Big|_{\mathbf{p}=\mathbf{p}_*} = \left(\begin{array}{c} -E_0 \\ H_0 \end{array} \right) \Big|_{p_z=p_{z*}}, \quad \left(\begin{array}{c} E_{\perp 2} \\ H_{\parallel 2} \end{array} \right) \Big|_{\mathbf{p}=\mathbf{p}_*} = \left(\begin{array}{c} -E_{02} \\ H_{02} \end{array} \right) \Big|_{p_z=p_{z*}}. \quad (27)$$

B. Floquet-Bloch solutions in an arbitrary coordinate system

We have found solutions $E_{\parallel}, H_{\perp}$ and $E_{\perp}, H_{\parallel}$ of the systems (17). These solutions were found in the coordinate system rotated by an angle γ , which characterizes the direction of

wave propagation. In the initial coordinate system, these solutions read:

$$\mathbf{\Phi}^H = \begin{pmatrix} E_{\parallel} \cos \gamma \\ E_{\parallel} \sin \gamma \\ -\frac{1}{k\varepsilon} p_{\parallel} H_{\perp} \\ -H_{\perp} \sin \gamma \\ H_{\perp} \cos \gamma \\ 0 \end{pmatrix}, \quad \mathbf{\Phi}^E = \begin{pmatrix} -E_{\perp} \sin \gamma \\ E_{\perp} \cos \gamma \\ 0 \\ H_{\parallel} \cos \gamma \\ H_{\parallel} \sin \gamma \\ \frac{1}{k\mu} p_{\parallel} E_{\perp} \end{pmatrix}. \quad (28)$$

The solutions (28) do not have a limit for $p_{\parallel} \rightarrow 0$ as a function of two variables p_x, p_y . This limit exists in any direction determined by γ and depends on the direction γ :

$$\mathbf{\Phi}^H|_{p_{\parallel} \rightarrow 0} \rightarrow \cos \gamma \mathbf{\Phi}^X - \sin \gamma \mathbf{\Phi}^Y, \quad \mathbf{\Phi}^E|_{p_{\parallel} \rightarrow 0} \rightarrow \sin \gamma \mathbf{\Phi}^X + \cos \gamma \mathbf{\Phi}^Y. \quad (29)$$

Here we take into account (19) and the definitions of $\mathbf{\Phi}^X$ and $\mathbf{\Phi}^Y$ from (21).

Below we will use the derivatives $\partial \mathbf{\Phi}^H / \partial p_j$, $\partial \mathbf{\Phi}^E / \partial p_j$, $j = x, y, z$, which are linear combinations of the derivatives of the functions $E_{\parallel}, H_{\perp}$ and $E_{\perp}, H_{\parallel}$. These functions are analytic functions of the parameter $p_{\parallel}^2$, since the coefficients of the system (17) are analytic functions of $p_{\parallel}^2$. It is easy to obtain

$$\frac{\partial E_{\parallel}}{\partial p_x} = 2p_{\parallel} \frac{\partial E_{\parallel}}{\partial p_{\parallel}^2} \cos \gamma. \quad (30)$$

This yields $\partial E_{\parallel} / \partial p_x|_{p_{\parallel}=0} = 0$. Similarly, we derive that the derivatives of $H_{\perp}$, $E_{\perp}$ and $H_{\parallel}$ with respect to the variables p_x and p_y are zero for $p_{\parallel} = 0$. Finally, we get

$$\frac{\partial \mathbf{\Phi}^H}{\partial p_x} \Big|_{p_x=p_y=0} = \frac{\partial \mathbf{\Phi}^H}{\partial p_y} \Big|_{p_x=p_y=0} = \left(0, 0, -\frac{H_0}{k\varepsilon}, 0, 0, 0 \right)^t, \quad (31)$$

$$\frac{\partial \mathbf{\Phi}^E}{\partial p_x} \Big|_{p_x=p_y=0} = \frac{\partial \mathbf{\Phi}^E}{\partial p_y} \Big|_{p_x=p_y=0} = \left(0, 0, 0, 0, 0, -\frac{E_0}{k\mu} \right)^t. \quad (32)$$

These derivatives do not depend on the direction γ .

We introduce the unified notation $\mathbf{\Phi}^f$ for the Floquet-Bloch solutions of different types:

$$\mathbf{\Phi}^f(z; \mathbf{p}) = e^{ip_z z} \boldsymbol{\varphi}^f(z; \mathbf{p}), \quad f = H, E, X, \text{ or } Y, \quad (33)$$

where $\boldsymbol{\varphi}^f(z + b; \mathbf{p}) = \boldsymbol{\varphi}^f(z; \mathbf{p})$. The six-component vector-functions $\boldsymbol{\varphi}^f(z, \mathbf{p})$ are called the Floquet-Bloch amplitudes. Let us discuss formula (33) in more detail. The Floquet-Bloch solutions $\mathbf{\Phi}^f(z; \mathbf{p})$ for $f = H, E$ are determined by formula (28), where $E_{\parallel}, H_{\perp}$ and $E_{\perp}, H_{\parallel}$ are the first solutions (22) of the systems (17). We assume that the frequency ω

in the formulas (22) is expressed in terms of $\mathbf{p}$ on one of the sheets of the multisheeted function $\omega = \omega^f(\mathbf{p})$. We also take into account the fact that $p_{\parallel}^2 = p_x^2 + p_y^2$, $\cos \gamma = p_x/p_{\parallel}$, $\sin \gamma = p_y/p_{\parallel}$. The number of the sheet is omitted for brevity. The Floquet-Bloch solutions $\Phi^f(z; \mathbf{p})$, $f = X, Y$, are defined only for $p_{\parallel} = 0$, i.e., for $\mathbf{p} = \mathbf{p}_0 \equiv (0, 0, p_z)$; their polarization is not defined.

The limit of the Floquet-Bloch amplitudes in the direction determined by γ follows from (29):

$$\varphi^H|_{p_{\parallel} \rightarrow 0} \rightarrow \cos \gamma \varphi^X - \sin \gamma \varphi^Y, \quad \varphi^E|_{p_{\parallel} \rightarrow 0} \rightarrow \sin \gamma \varphi^X + \cos \gamma \varphi^Y. \quad (34)$$

In particular, if $\gamma = 0$, then $p_{\parallel} = p_x$. If $\gamma = \pi/2$, then $p_{\parallel} = p_y$. From (34) we obtain

$$\varphi^H(z; \mathbf{p})|_{p_x \rightarrow 0, p_y = 0} \rightarrow \varphi^X(z; \mathbf{p}_0), \quad \varphi^E(z; \mathbf{p})|_{p_x \rightarrow 0, p_y = 0} \rightarrow \varphi^Y(z; \mathbf{p}_0), \quad (35)$$

$$\varphi^H(z; \mathbf{p})|_{p_x = 0, p_y \rightarrow 0} \rightarrow -\varphi^Y(z; \mathbf{p}_0), \quad \varphi^E(z; \mathbf{p})|_{p_x = 0, p_y \rightarrow 0} \rightarrow \varphi^X(z; \mathbf{p}_0). \quad (36)$$

Next, we need to obtain the derivatives of the solutions φ^H and φ^E with respect to the parameters p_x and p_y at the point $p_{\parallel} = 0$. Owing to (31) and (32) and the definition (33), we get

$$\frac{\partial \varphi^H}{\partial p_x} \Big|_{\mathbf{p}_*} = \frac{\partial \varphi^H}{\partial p_y} \Big|_{\mathbf{p}_*} = \left(0, 0, -\frac{H_0}{k\varepsilon}, 0, 0, 0 \right)^t \Big|_{p_{z*}} e^{-ip_{z*}z}, \quad (37)$$

$$\frac{\partial \varphi^E}{\partial p_x} \Big|_{\mathbf{p}_*} = \frac{\partial \varphi^E}{\partial p_y} \Big|_{\mathbf{p}_*} = \left(0, 0, 0, 0, 0, -\frac{E_0}{k\mu} \right)^t \Big|_{p_{z*}} e^{-ip_{z*}z}. \quad (38)$$

These derivatives do not depend on the direction γ . These functions are periodic in z , because φ^H , φ^E are periodic for all $\mathbf{p}$.

V. SOME AUXILIARY RELATIONS

Our aim is to obtain relations for the derivatives of the dispersion functions by means of the Floquet-Bloch amplitudes. To do this, we give equations for these amplitudes and their derivatives with respect to the parameters p_j , $j = x, y, z$.

A. Equations for the Floquet-Bloch amplitudes and their derivatives

We deal with six-component solutions of the Maxwell equations:

$$\Psi_B^f(x, y, z; \mathbf{p}) = e^{i(p_x x + p_y y)} \Phi^f(z; \mathbf{p}), \quad f = E, H, \quad (39)$$

where Φ^f is of the form (33). Here the superscript f stands for the type of the field: $f = E$ corresponds to the TE polarization and $f = H$ corresponds to the TM one. Inserting (39) into Maxwell equations, we rewrite them in the form

$$\mathcal{A}^f(\mathbf{p})\varphi^f(z; \mathbf{p}) = 0, \quad (40)$$

where

$$\mathcal{A}^f(\mathbf{p}) \equiv \frac{\omega^f(\mathbf{p})}{c} \mathbf{P} + i\Gamma_3 \frac{\partial}{\partial z} - \mathbf{p} \cdot \hat{\Gamma}, \quad \mathbf{p} \cdot \hat{\Gamma} \equiv p_x \Gamma_1 + p_y \Gamma_2 + p_z \Gamma_3. \quad (41)$$

We note that the equations for both types differ only by the dispersion function $\omega^f(\mathbf{p})$. These equations are valid for any $\mathbf{p}$, and thus we can take the derivatives of these equations with respect to $\mathbf{p}$. By taking the derivatives with respect to parameters $p_j, j = x, y$, we obtain

$$\mathcal{A}^f(\mathbf{p}) \frac{\partial \varphi^f}{\partial p_j} = - \frac{\partial \mathcal{A}^f}{\partial p_j} \varphi^f, \quad (42)$$

$$\mathcal{A}^f(\mathbf{p}) \frac{\partial^2 \varphi^f}{\partial p_j^2} = - \frac{1}{c} \frac{\partial^2 \omega^f}{\partial p_j^2} \mathbf{P} \varphi^f - 2 \frac{\partial \mathcal{A}^f(\mathbf{p})}{\partial p_j} \frac{\partial \varphi^f}{\partial p_j}, \quad (43)$$

where

$$\frac{\partial \mathcal{A}^f}{\partial p_j} = \frac{1}{c} \frac{\partial \omega^f}{\partial p_j} \mathbf{P} - \Gamma_j. \quad (44)$$

The derivatives with respect to p_z are discussed below at the end of the Section. Now we proceed with specifying formulas (42), (44) at the stationary points $\mathbf{p}_*$. Such points for each branch of the multisheeted dispersion functions $\omega^f(\mathbf{p})$, $f = E, H$, differ only by p_{z*} , and all of them have $p_{\parallel*} = 0$. Solutions $\varphi^f(z; \mathbf{p})$ are not continuous as functions of two variables p_x and p_y near the point $p_x = p_y = 0$. However, for any fixed angle γ , they can be calculated by means of the passage to the limit, see (34). The derivatives at $p_{\parallel} = 0$ do not depend on γ , see (37), (38). We indicate these derivatives at $\mathbf{p} = \mathbf{p}_*$ by the asterisk subscript. Upon substitution $\mathbf{p} = \mathbf{p}_*$, the operator $\mathcal{A}$ is denoted as

$$\mathcal{A}^f(\mathbf{p}_*) \equiv \mathcal{A}_*(\mathbf{p}_*), \quad f = E, H, \quad (45)$$

and no more depends on the wave type TM or TE.

Let $\mathcal{M}$ be a class of six-component vector-valued functions of z , which are periodic with a period b , piecewise smooth on the period and their components with numbers 1, 2, 4, 5 are continuous; see details in Appendix 2. Lemma 1 (see Appendix 2) shows that the operator $\mathcal{A}_*(\mathbf{p}_*)$ is symmetric on the functions from $\mathcal{M}$.

Finally, passing to the limit in (42), (44), in view of (35), (36) we obtain

$$\mathcal{A}_* \frac{\partial \varphi_*^H}{\partial p_x} = \Gamma_1 \varphi_*^X, \quad \mathcal{A}_* \frac{\partial \varphi_*^E}{\partial p_x} = \Gamma_1 \varphi_*^Y, \quad (46)$$

$$\mathcal{A}_* \frac{\partial \varphi_*^H}{\partial p_y} = -\Gamma_2 \varphi_*^Y, \quad \mathcal{A}_* \frac{\partial \varphi_*^E}{\partial p_y} = \Gamma_2 \varphi_*^X. \quad (47)$$

Here we have introduced the notation

$$\varphi^X(z; \mathbf{p}_*) = \varphi_*^X, \quad \varphi^Y(z; \mathbf{p}_*) = \varphi_*^Y. \quad (48)$$

We note that the terms containing the derivative $\partial \omega^f / \partial p_j$ vanish at the stationary point, since this derivative vanishes.

For the second derivatives of the Floquet-Bloch amplitudes, in view of (43), (44), and (35), (36) we derive

$$\mathcal{A}_* \frac{\partial^2 \varphi_*^H}{\partial p_x^2} = -\frac{1}{c} \frac{\partial^2 \omega_*^H}{\partial p_x^2} \mathbf{P} \varphi_*^X + 2\Gamma_1 \frac{\partial \varphi_*^H}{\partial p_x}, \quad (49)$$

$$\mathcal{A}_* \frac{\partial^2 \varphi_*^E}{\partial p_x^2} = -\frac{1}{c} \frac{\partial^2 \omega_*^E}{\partial p_x^2} \mathbf{P} \varphi_*^Y + 2\Gamma_1 \frac{\partial \varphi_*^E}{\partial p_x}, \quad (50)$$

$$\mathcal{A}_* \frac{\partial^2 \varphi_*^H}{\partial p_y^2} = \frac{1}{c} \frac{\partial^2 \omega_*^H}{\partial p_y^2} \mathbf{P} \varphi_*^Y + 2\Gamma_2 \frac{\partial \varphi_*^H}{\partial p_y}, \quad (51)$$

$$\mathcal{A}_* \frac{\partial^2 \varphi_*^E}{\partial p_y^2} = -\frac{1}{c} \frac{\partial^2 \omega_*^E}{\partial p_y^2} \mathbf{P} \varphi_*^X + 2\Gamma_2 \frac{\partial \varphi_*^E}{\partial p_y}. \quad (52)$$

We emphasize that the directional limit of φ^H and φ^E at the point $\mathbf{p}_*$ can be expressed by φ_*^X , as well as by φ_*^Y depending on the direction γ .

Now we proceed to the calculation of the derivatives with respect to p_z at the point $\mathbf{p}_*$, i.e., $p_{\parallel*} = 0$, $p_z = p_{z*}$. If $p_{\parallel} = p_{\parallel*} = 0$, i.e., $\mathbf{p} = \mathbf{p}_0 \equiv (0, 0, p_z)$, we have

$$\omega^H(\mathbf{p}_0) = \omega^E(\mathbf{p}_0) \equiv \omega^0(\mathbf{p}_0) \quad (53)$$

and $\mathcal{A}^H(\mathbf{p}_0) = \mathcal{A}^E(\mathbf{p}_0) \equiv \mathcal{A}^0(\mathbf{p}_0)$. The Floquet-Bloch amplitudes φ^X , φ^Y (see (33), (21)) satisfy the same equation

$$\mathcal{A}^0(\mathbf{p}_0) \varphi^f(z; \mathbf{p}_0) = 0, \quad f = X, Y. \quad (54)$$

By differentiating (54) with respect to p_z and then by passing to the limit $p_z \rightarrow p_{z*}$, we get

$$\mathcal{A}_* \frac{\partial \varphi_*^X}{\partial p_z} = \Gamma_3 \varphi_*^X, \quad \mathcal{A}_* \frac{\partial \varphi_*^Y}{\partial p_z} = \Gamma_3 \varphi_*^Y. \quad (55)$$

By taking the second derivatives of (54) and then by passing to the limit $p_z \rightarrow p_{z*}$, we obtain

$$\mathcal{A}_* \frac{\partial^2 \varphi_*^X}{\partial p_z^2} = -\frac{1}{c} \frac{\partial^2 \omega_*^0}{\partial p_z^2} \mathbf{P} \varphi_*^X + 2\Gamma_3 \frac{\partial \varphi_*^X}{\partial p_z}, \quad (56)$$

$$\mathcal{A}_* \frac{\partial^2 \varphi_*^Y}{\partial p_z^2} = -\frac{1}{c} \frac{\partial^2 \omega_*^0}{\partial p_z^2} \mathbf{P} \varphi_*^Y + 2\Gamma_3 \frac{\partial \varphi_*^Y}{\partial p_z}. \quad (57)$$

B. Derivatives of dispersion functions

Now we get integral relations containing derivatives of the Floquet-Bloch amplitudes and derivatives of dispersion functions. We take the inner product of (46), (47), and (55) with φ_*^X or φ_*^Y and, taking into account the fact that

$$\mathcal{A}_* \varphi_*^X = 0, \quad \mathcal{A}_* \varphi_*^Y = 0, \quad (58)$$

by Lemma 1 (see Appendix 2) we find

$$(\varphi_*^{f_2}, \Gamma_j \varphi_*^{f_1}) = 0 \quad \text{for any } j = 1, 2, 3; \quad f_1 = X, Y; \quad f_2 = X, Y. \quad (59)$$

Henceforth, we use the fact that φ^{f_2} and its derivatives with respect to parameters p_j , $j = x, y, z$ belong to $\mathcal{M}$.

We are going to apply the same operations to formulas (49–52) and (56–57). We introduce the notation

$$u_*^{f_1 f_2} \equiv (\varphi_*^{f_1}, \mathbf{P} \varphi_*^{f_2}), \quad f_1 = X \text{ or } Y, \quad f_2 = X \text{ or } Y, \quad (60)$$

where u^{ff} has the meaning of the density of energy averaged over time (see Section III), and

$$\ddot{\omega}_{11*}^f \equiv \left. \frac{\partial^2 \omega^f}{\partial p_x^2} \right|_{\mathbf{p}=\mathbf{p}*}, \quad \ddot{\omega}_{22*}^f \equiv \left. \frac{\partial^2 \omega^f}{\partial p_y^2} \right|_{\mathbf{p}=\mathbf{p}*}, \quad f = H \text{ or } E; \quad \ddot{\omega}_{33*}^0 \equiv \left. \frac{\partial^2 \omega^0}{\partial p_z^2} \right|_{\mathbf{p}=\mathbf{p}*}, \quad (61)$$

where $\ddot{\omega}_{33*}^0 = \ddot{\omega}_{33*}^H = \ddot{\omega}_{33*}^E$, because (53) is valid for any p_z . We arrive at the relations

$$\frac{\ddot{\omega}_{11*}^H}{c} u_*^{XX} = 2 \left(\varphi_*^X, \Gamma_1 \frac{\partial \varphi_*^H}{\partial p_x} \right), \quad \frac{\ddot{\omega}_{11*}^E}{c} u_*^{YY} = 2 \left(\varphi_*^Y, \Gamma_1 \frac{\partial \varphi_*^E}{\partial p_x} \right), \quad (62)$$

$$\frac{\ddot{\omega}_{22*}^H}{c} u_*^{YY} = -2 \left(\varphi_*^Y, \Gamma_2 \frac{\partial \varphi_*^H}{\partial p_y} \right), \quad \frac{\ddot{\omega}_{22*}^E}{c} u_*^{XX} = 2 \left(\varphi_*^X, \Gamma_2 \frac{\partial \varphi_*^E}{\partial p_y} \right), \quad (63)$$

$$\frac{\ddot{\omega}_{33*}^0}{c} u_*^{XX} = 2 \left(\varphi_*^X, \Gamma_3 \frac{\partial \varphi_*^X}{\partial p_z} \right), \quad \frac{\ddot{\omega}_{33*}^0}{c} u_*^{YY} = 2 \left(\varphi_*^Y, \Gamma_3 \frac{\partial \varphi_*^Y}{\partial p_z} \right). \quad (64)$$

If $f_1 \neq f_2$, then $u^{f_1 f_2} \equiv 0$. Moreover, $u^{XX} = u^{YY}$ by the definitions of φ_*^X , φ_*^Y , and $\mathbf{P}$.

C. Additional relations

Multiplying equations (46), (47) and (55) by φ_*^X and φ_*^Y in such a way that on the left-hand side we obtain $(\varphi_*^X, \mathbf{P}\varphi_*^Y)$, which vanishes, we find the following relations:

$$\left(\varphi_*^Y, \Gamma_1 \frac{\partial \varphi_*^H}{\partial p_x}\right) = \left(\varphi_*^X, \Gamma_1 \frac{\partial \varphi_*^E}{\partial p_x}\right) = \left(\varphi_*^Y, \Gamma_2 \frac{\partial \varphi_*^H}{\partial p_y}\right) = 0, \quad (65)$$

$$\left(\varphi_*^X, \Gamma_2 \frac{\partial \varphi_*^E}{\partial p_y}\right) = \left(\varphi_*^Y, \Gamma_3 \frac{\partial \varphi_*^X}{\partial p_z}\right) = \left(\varphi_*^X, \Gamma_3 \frac{\partial \varphi_*^Y}{\partial p_z}\right) = 0. \quad (66)$$

Now we mention some other useful relations with the derivatives of φ^f . The derivatives of φ^f with respect to p_x and p_y coincide; see (31) and (32). This fact yields

$$\Gamma_1 \varphi_*^X = -\Gamma_2 \varphi_*^Y, \quad \Gamma_1 \varphi_*^Y = \Gamma_2 \varphi_*^X. \quad (67)$$

The same relations can be obtained by direct computations by (21), (7) not only at the point $\mathbf{p}_*$ but at the point $\mathbf{p} = (0, 0, p_z)$ for any p_z . The direct calculations with the help of (31), (32) and (7) show that

$$\Gamma_3 \frac{\partial \varphi_*^H}{\partial p_j} = 0, \quad \Gamma_3 \frac{\partial \varphi_*^E}{\partial p_j} = 0, \quad j = x, y. \quad (68)$$

VI. THE TWO-SCALED ASYMPTOTIC DECOMPOSITION

We give an asymptotic representation of some special solutions of Maxwell equations in the entire space under several assumptions:

1. the vertical period b of the medium is small as compared with the horizontal scale of the field, and the relation between the scales is characterized by the small parameter χ ,
2. the frequency ω is close to the frequency ω_* of the stationary point $\mathbf{p}_*$ of one of the sheets of the dispersion function $\omega = \omega^f(\mathbf{p})$, $f = H, E$, i.e., the frequency ω_* is determined by the relations

$$\omega_* = \omega^E(\mathbf{p}_*) = \omega^H(\mathbf{p}_*), \quad \nabla \omega^f(\mathbf{p}_*) = 0, \quad f = H, E. \quad (69)$$

We assume that

$$\omega = \omega_* + \chi^2 \delta\omega, \quad \delta\omega \sim 1. \quad (70)$$

3. We assume that there is one bounded and one unbounded Floquet-Bloch solution of the periodic problem (18) at the point $\mathbf{p}_*$.

Our aim is to find the asymptotics of solutions of the Maxwell equations in the following form:

$$\Psi = \Psi(z, \boldsymbol{\rho}), \quad \xi \equiv \chi x, \quad \eta \equiv \chi y, \quad \zeta \equiv \chi z, \quad \boldsymbol{\rho} = (\xi, \eta, \zeta) \quad (71)$$

where $\chi \ll 1$. In the direction transverse to the layers, the field has two scales, one of them is determined by the slow variable $\zeta = \chi z$, and the other is given by the variable z . In the plane of the layers in the directions x and y , the field depends only on the slow variables $\xi = \chi x$, $\eta = \chi y$.

We seek a solution in the form of a two-scaled asymptotic series

$$\Psi(z, \boldsymbol{\rho}) = \Phi(z, \boldsymbol{\rho}) e^{i(p_{x*}\xi + p_{y*}\eta)/\chi}, \quad \Phi(z, \boldsymbol{\rho}) = \phi(z, \boldsymbol{\rho}) e^{ip_{z*}z}, \quad (72)$$

$$\phi(z, \boldsymbol{\rho}) = \sum_{n \geq 0} \chi^n \phi^{(n)}(z, \boldsymbol{\rho}), \quad \phi^{(n)}(z + b, \boldsymbol{\rho}) = \phi^{(n)}(z, \boldsymbol{\rho}), \quad \boldsymbol{\rho} = (\xi, \eta, \zeta). \quad (73)$$

In the case under consideration, the stationary point is $p_{x*} = p_{y*} = 0$.

We assume that $\phi^{(n)} \in \mathcal{M}$ for every n as functions of z , see the definition after formula (45). Also these functions are infinitely differentiable with respect to slow variables.

The Maxwell equations in new variables read

$$k_* \mathbf{P} \Psi + i \Gamma_3 \frac{\partial \Psi}{\partial z} = -i \chi \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \Psi - \chi^2 \frac{\delta \omega}{c} \mathbf{P} \Psi, \quad k_* = \frac{\omega_*}{c}, \quad (74)$$

where

$$\hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \equiv \Gamma_1 \frac{\partial}{\partial \xi} + \Gamma_2 \frac{\partial}{\partial \eta} + \Gamma_3 \frac{\partial}{\partial \zeta}.$$

Substituting the asymptotic series (72) in (74), we obtain a set of equations

$$\mathcal{A}_* \phi^{(0)} = 0, \quad \mathcal{A}_* \phi^{(n)} = \mathbf{F}^{(n)}, \quad (75)$$

where

$$\mathcal{A}_* \Psi = k_* \mathbf{P} \Psi + i \Gamma_3 \frac{\partial \Psi}{\partial z} - p_{3*} \Gamma_3 \Psi, \quad (76)$$

$$\mathbf{F}^{(1)} = -i \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \phi^{(0)}, \quad (77)$$

$$\mathbf{F}^{(n)} = -i \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \phi^{(n-1)} - \frac{\delta \omega}{c} \mathbf{P} \phi^{(n-2)}, \quad n \geq 2. \quad (78)$$

Prior to solving the set of equations, we are going to find the relations between the parameters of the problem, which ensures that all nonzero terms on the right-hand side of

(76) are of the same order. We assume that the variables $\mathbb{E}$ and $\mathbb{H}$ and the parameters ε and μ in formulas (1) are already normalized as follows

$$\mathbb{E} = \sqrt{\frac{\varepsilon_{av}}{\mu_{av}}} \tilde{\mathbb{E}}, \quad \mathbb{H} = \sqrt{\frac{\varepsilon_{av}}{\mu_{av}}} \tilde{\mathbb{H}}, \quad \text{where} \quad \varepsilon = \frac{\tilde{\varepsilon}}{\varepsilon_{av}}, \quad \mu = \frac{\tilde{\mu}}{\mu_{av}}, \quad k_* = \sqrt{\varepsilon_{av} \mu_{av}} \tilde{k}_*,$$

where ε_{av} , μ_{av} are typical dielectric permittivity and magnetic permeability, these parameters may be large, ε and μ are of order unity, and $\tilde{\varepsilon}, \tilde{\mu}$ are the original parameters of the equation. The variables $\tilde{k}_*$ and k_* mean the wave number in vacuum and in the medium with parameters ε_{av} and μ_{av} , respectively, $k_* = \sqrt{\varepsilon_{av} \mu_{av}} \omega / c$, where c is the speed of light in vacuum. The second and the third (if nonzero) terms in the right-hand side of (76) are of order of $1/b$. The first and the second terms are of the same order if

$$\sqrt{\varepsilon_{av} \mu_{av}} \omega / c \sim 1/b. \quad (79)$$

This means that the case under consideration differs from the well-known case $\omega b / c \rightarrow 0$.

A. The principal order

The equation of principal order term is the equation for the Floquet-Bloch amplitudes at the stationary point $\mathbf{p}_*$. It does not contain the derivatives with respect to slow variables $\boldsymbol{\rho} = (\xi, \eta, \zeta)$ and its coefficients do not depend on $\boldsymbol{\rho}$. Its solutions may depend on $\boldsymbol{\rho}$ as on parameters. We seek the principal term in the form of

$$\boldsymbol{\phi}^{(0)}(z, \boldsymbol{\rho}) = \alpha_1(\boldsymbol{\rho}) \boldsymbol{\varphi}_*^X(z) + \alpha_2(\boldsymbol{\rho}) \boldsymbol{\varphi}_*^Y(z), \quad \boldsymbol{\phi}^{(0)} \in \mathcal{M}, \quad (80)$$

where

$$\boldsymbol{\varphi}_*^f(z) = \boldsymbol{\varphi}^f(z; \mathbf{p}_*) = e^{-ip_{z*}z} \boldsymbol{\Phi}^f(z; \mathbf{p}_*), \quad (81)$$

$f = X, Y$, and $\boldsymbol{\Phi}^f(z; \mathbf{p})$ for $p_{\parallel} = 0$ are defined in (21) by means of the functions E_0 and H_0 , which satisfy a system (18). The functions α_1, α_2 are arbitrary scalar functions of slow variables $\boldsymbol{\rho}$. Additional restrictions on these arbitrary functions will arise later.

B. First-order approximation

The equation for the first-order term $\boldsymbol{\phi}^{(1)}$ of the expansion has the form

$$\mathcal{A}_* \boldsymbol{\phi}^{(1)} = -i \hat{\boldsymbol{\Gamma}} \cdot \nabla_{\boldsymbol{\rho}} \boldsymbol{\phi}^{(0)}, \quad \boldsymbol{\phi}^{(1)} \in \mathcal{M}. \quad (82)$$

In order to get the solution of the system belonging to the class $\mathcal{M}$, we must impose additional conditions.

Lemma 2. A solution from the class $\mathcal{M}$ of the equation $\mathcal{A}_*\phi = \mathbf{F}$ exists if and only if the following conditions are satisfied:

$$(\varphi_*^X, \mathbf{F}) = 0, \quad (\varphi_*^Y, \mathbf{F}) = 0. \quad (83)$$

The proof of the Lemma 2 is given in the Appendix 2.

Now we check the solvability conditions for the first-order approximation (82), i.e., we must check that

$$(\varphi_*^X, \hat{\Gamma} \cdot \nabla_\rho \phi^{(0)}) = 0, \quad (\varphi_*^Y, \hat{\Gamma} \cdot \nabla_\rho \phi^{(0)}) = 0, \quad (84)$$

which are reduced to the following conditions

$$(\varphi_*^X, \hat{\Gamma} \varphi_*^X) \cdot \nabla_\rho \alpha_1 + (\varphi_*^X, \hat{\Gamma} \varphi_*^Y) \cdot \nabla_\rho \alpha_2 = 0, \quad (85)$$

$$(\varphi_*^Y, \hat{\Gamma} \varphi_*^X) \cdot \nabla_\rho \alpha_1 + (\varphi_*^Y, \hat{\Gamma} \varphi_*^Y) \cdot \nabla_\rho \alpha_2 = 0, \quad (86)$$

where, for example,

$$(\varphi_*^X, \hat{\Gamma} \varphi_*^X) \cdot \nabla_\rho \alpha_1 \equiv (\varphi_*^X, \Gamma_1 \varphi_*^X) \frac{\partial \alpha_1}{\partial \xi} + (\varphi_*^X, \Gamma_2 \varphi_*^X) \frac{\partial \alpha_1}{\partial \eta} + (\varphi_*^X, \Gamma_3 \varphi_*^X) \frac{\partial \alpha_1}{\partial \zeta}. \quad (87)$$

These conditions are satisfied at the stationary point owing to (59).

Now let us find the exact formula for the solution $\phi^{(1)}$. The right-hand side of the equation (82) can be written as follows:

$$\mathbf{F}^{(1)} = -i \hat{\Gamma} \cdot (\nabla_\rho \alpha_1) \varphi_*^X - i \hat{\Gamma} \cdot (\nabla_\rho \alpha_2) \varphi_*^Y. \quad (88)$$

Taking into account (67), we replace the terms containing Γ_2 by the terms containing Γ_1 .

Collecting the resulting terms, we obtain

$$\mathbf{F}^{(1)} = -i \left(\frac{\partial \alpha_1}{\partial \xi} - \frac{\partial \alpha_2}{\partial \eta} \right) \Gamma_1 \varphi_*^X - i \left(\frac{\partial \alpha_1}{\partial \eta} + \frac{\partial \alpha_2}{\partial \xi} \right) \Gamma_1 \varphi_*^Y - i \frac{\partial \alpha_1}{\partial \zeta} \Gamma_3 \varphi_*^X - i \frac{\partial \alpha_2}{\partial \zeta} \Gamma_3 \varphi_*^Y. \quad (89)$$

Now the right-hand side contains four terms. Instead of solving (82), we solve four independent vector equations with right-hand sides containing each of the terms and then take the sum of their solutions. We add also a solution of the homogeneous equation. The particular solutions of four equations coincide with solutions of (46), (47), and (55). We find the following solution:

$$\begin{aligned} \phi^{(1)} = & -i \left(\frac{\partial \alpha_1}{\partial \xi} - \frac{\partial \alpha_2}{\partial \eta} \right) \frac{\partial \varphi_*^H}{\partial p_x} - i \left(\frac{\partial \alpha_1}{\partial \eta} + \frac{\partial \alpha_2}{\partial \xi} \right) \frac{\partial \varphi_*^E}{\partial p_x} \\ & - i \frac{\partial \alpha_1}{\partial \zeta} \frac{\partial \varphi_*^X}{\partial p_z} - i \frac{\partial \alpha_2}{\partial \zeta} \frac{\partial \varphi_*^Y}{\partial p_z} + \alpha_1^{(1)} \varphi_*^X(z) + \alpha_2^{(1)} \varphi_*^Y(z), \end{aligned} \quad (90)$$

where $\alpha_{1,2}^{(1)}$ are new arbitrary functions of the slow variables $\boldsymbol{\rho} = (\xi, \eta, \zeta)$. The subscript $*$ stands to show that all the derivatives with the respect to $p_j, j = x, y, z$ are taken at $\boldsymbol{p} = \boldsymbol{p}_*$.

C. The second-order approximation

Now let us consider the equation on the second-order approximation

$$\mathcal{A}_* \phi^{(2)} = -i \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \phi^{(1)}, \quad \phi^{(2)} \in \mathcal{M}. \quad (91)$$

The solution $\phi^{(1)}$ depends on four unknown functions $\alpha_j, j = 1, 2$ and $\alpha_j^{(1)}, j = 1, 2$. The solvability conditions of (91) yield equations for two of them:

$$i \left(\varphi_*^X, \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \phi^{(1)} \right) + \left(\varphi_*^X, \frac{\delta \omega}{c} \mathbf{P} \phi^{(0)} \right) = 0, \quad (92)$$

$$i \left(\varphi_*^Y, \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \phi^{(1)} \right) + \left(\varphi_*^Y, \frac{\delta \omega}{c} \mathbf{P} \phi^{(0)} \right) = 0. \quad (93)$$

For brevity, we introduce the notation

$$\tau_1 \equiv \left(\frac{\partial \alpha_1}{\partial \xi} - \frac{\partial \alpha_2}{\partial \eta} \right), \quad \tau_2 \equiv \left(\frac{\partial \alpha_1}{\partial \eta} + \frac{\partial \alpha_2}{\partial \xi} \right). \quad (94)$$

Let us calculate every term separately

$$\begin{aligned} i \left(\varphi_*^X, \hat{\Gamma} \cdot \nabla_{\boldsymbol{\rho}} \phi^{(1)} \right) &= \left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^H}{\partial p_x} \right) \cdot \nabla_{\boldsymbol{\rho}} \tau_1 + \left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^E}{\partial p_x} \right) \cdot \nabla_{\boldsymbol{\rho}} \tau_2 \\ &+ \left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^X}{\partial p_z} \right) \cdot \nabla_{\boldsymbol{\rho}} \frac{\partial \alpha_1}{\partial \zeta} + \left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^Y}{\partial p_z} \right) \cdot \nabla_{\boldsymbol{\rho}} \frac{\partial \alpha_2}{\partial \zeta}. \end{aligned} \quad (95)$$

Here we take into account that the coefficients of $\alpha_2^{(1)}$ and $\alpha_1^{(1)}$ vanish owing to (59).

For example, the first term in the right-hand side of (95) reads

$$\begin{aligned} \left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^H}{\partial p_x} \right) \cdot \nabla_{\boldsymbol{\rho}} \tau_1 &\equiv \\ &\left(\varphi_*^X, \Gamma_1 \frac{\partial \varphi_*^H}{\partial p_x} \right) \frac{\partial \tau_1}{\partial \xi} + \left(\varphi_*^X, \Gamma_2 \frac{\partial \varphi_*^H}{\partial p_x} \right) \frac{\partial \tau_1}{\partial \eta} + \left(\varphi_*^X, \Gamma_3 \frac{\partial \varphi_*^H}{\partial p_x} \right) \frac{\partial \tau_1}{\partial \zeta}. \end{aligned} \quad (96)$$

According to (62), the first term is proportional to $\ddot{\omega}_{11*}^H$. The second term vanishes owing to (31) and the last relation of (65), the third term vanishes by (68). Analogously,

$$\begin{aligned} \left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^E}{\partial p_x} \right) \cdot \nabla_{\boldsymbol{\rho}} \tau_2 &\equiv \\ &\left(\varphi_*^X, \Gamma_1 \frac{\partial \varphi_*^E}{\partial p_x} \right) \frac{\partial \tau_2}{\partial \xi} + \left(\varphi_*^X, \Gamma_2 \frac{\partial \varphi_*^E}{\partial p_x} \right) \frac{\partial \tau_2}{\partial \eta} + \left(\varphi_*^X, \Gamma_3 \frac{\partial \varphi_*^E}{\partial p_x} \right) \frac{\partial \tau_2}{\partial \zeta}. \end{aligned} \quad (97)$$

According to (63), the second term is proportional to $\ddot{\omega}_{22*}^E$ and two other terms vanish: the first one owing to (65), and the third one because of (68).

Now we proceed to the last two terms in (95). By (64)-(66), we obtain

$$\left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^X}{\partial p_z}\right) \cdot \nabla_\rho \frac{\partial \alpha_1}{\partial \zeta} = \left(\varphi_*^X, \Gamma_3 \frac{\partial \varphi_*^X}{\partial p_z}\right) \frac{\partial^2 \alpha_1}{\partial \zeta^2} = \frac{\ddot{\omega}_{33*}^0}{2c} u_*^{XX} \frac{\partial^2 \alpha_1}{\partial \zeta^2}, \quad (98)$$

$$\left(\varphi_*^X, \hat{\Gamma} \frac{\partial \varphi_*^Y}{\partial p_z}\right) \cdot \nabla_\rho \frac{\partial \alpha_2}{\partial \zeta} = \left(\varphi_*^X, \Gamma_3 \frac{\partial \varphi_*^Y}{\partial p_z}\right) \frac{\partial^2 \alpha_2}{\partial \zeta^2} = 0. \quad (99)$$

We note that since $u_*^{XY} = 0$, we get, with account of (80) and (60),

$$\left(\varphi_*^X, \frac{\delta \omega}{c} \mathbf{P} \phi^{(0)}\right) = \frac{\delta \omega}{c} u_*^{XX} \alpha_1. \quad (100)$$

Finally, the condition (92) yields

$$\frac{\partial \tau_1}{\partial \xi} \ddot{\omega}_{11*}^H + \frac{\partial \tau_2}{\partial \eta} \ddot{\omega}_{22*}^E + \frac{\partial^2 \alpha_1}{\partial \zeta^2} \ddot{\omega}_{33*}^0 + 2 \frac{\delta \omega}{c} \alpha_1 = 0. \quad (101)$$

We omit here the nonzero common factor $u_*^{XX}/2 = u_*^{YY}/2$.

Now we obtain the second equation by considering the condition (93). We use a similar line of argument. First, we take the relation that differs from (95) only by the first factor in inner products

$$\begin{aligned} i \left(\varphi_*^Y, \hat{\Gamma} \cdot \nabla_\rho \phi^{(1)}\right) &= \left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^H}{\partial p_x}\right) \cdot \nabla_\rho \tau_1 + \left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^E}{\partial p_x}\right) \cdot \nabla_\rho \tau_2 \\ &+ \left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^X}{\partial p_z}\right) \cdot \nabla_\rho \frac{\partial \alpha_1}{\partial \zeta} + \left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^Y}{\partial p_z}\right) \cdot \nabla_\rho \frac{\partial \alpha_2}{\partial \zeta}. \end{aligned} \quad (102)$$

Here, for example,

$$\begin{aligned} \left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^H}{\partial p_x}\right) \cdot \nabla_\rho \tau_1 &\equiv \\ \left(\varphi_*^Y, \Gamma_1 \frac{\partial \varphi_*^H}{\partial p_x}\right) \frac{\partial \tau_1}{\partial \xi} &+ \left(\varphi_*^Y, \Gamma_2 \frac{\partial \varphi_*^H}{\partial p_x}\right) \frac{\partial \tau_1}{\partial \eta} + \left(\varphi_*^Y, \Gamma_3 \frac{\partial \varphi_*^H}{\partial p_x}\right) \frac{\partial \tau_1}{\partial \zeta}. \end{aligned} \quad (103)$$

The second term here is proportional to $\ddot{\omega}_{22*}^H$ according to (63). The first and the third terms vanish by (65) and (68), respectively. The term $\left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^E}{\partial p_x}\right) \cdot \nabla_\rho \tau_2$ is treated analogously to (97) by using the second relation of (62), (66) with (47), and (68). Analogously to (98) and (99), we obtain

$$\left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^X}{\partial p_z}\right) \cdot \nabla_\rho \frac{\partial \alpha_1}{\partial \zeta} = 0, \quad \left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^Y}{\partial p_z}\right) \cdot \nabla_\rho \frac{\partial \alpha_2}{\partial \zeta} = \frac{\ddot{\omega}_{33*}^0}{2c} u_*^{XX} \frac{\partial^2 \alpha_2}{\partial \zeta^2}. \quad (104)$$

$$\left(\varphi_*^Y, \hat{\Gamma} \frac{\partial \varphi_*^H}{\partial p_x}\right) \cdot \nabla_\rho \tau_1 = -\frac{\ddot{\omega}_{22*}^H}{2c} u_*^{XX} \frac{\partial \tau_1}{\partial \eta}. \quad (105)$$

Again, by (65) and (66), we get

$$-\frac{\partial\tau_1}{\partial\eta}\ddot{\omega}_{22*}^H + \frac{\partial\tau_2}{\partial\xi}\ddot{\omega}_{11*}^E + \frac{\partial^2\alpha_2}{\partial\zeta^2}\ddot{\omega}_{33*}^0 + 2\frac{\delta\omega}{c}\alpha_2 = 0. \quad (106)$$

Taking into account the definition of τ_1 and τ_2 (94) and the fact that $\ddot{\omega}_{11*}^H = \ddot{\omega}_{22*}^H$ and $\ddot{\omega}_{11*}^E = \ddot{\omega}_{22*}^E$, we rewrite the equations for α_1 and α_2 as follows:

$$\begin{aligned} \frac{\partial^2\alpha_1}{\partial\xi^2}\ddot{\omega}_{11*}^H + \frac{\partial^2\alpha_1}{\partial\eta^2}\ddot{\omega}_{11*}^E + \frac{\partial^2\alpha_1}{\partial\zeta^2}\ddot{\omega}_{33*}^0 + 2\frac{\delta\omega}{c}\alpha_1 - \frac{\partial^2\alpha_2}{\partial\xi\partial\eta}(\ddot{\omega}_{11}^H - \ddot{\omega}_{11}^E) &= 0, \\ \frac{\partial^2\alpha_2}{\partial\zeta^2}\ddot{\omega}_{11*}^E + \frac{\partial^2\alpha_2}{\partial\eta^2}\ddot{\omega}_{11*}^H + \frac{\partial^2\alpha_2}{\partial\zeta^2}\ddot{\omega}_{33*}^0 + 2\frac{\delta\omega}{c}\alpha_2 - \frac{\partial^2\alpha_1}{\partial\xi\partial\eta}(\ddot{\omega}_{11}^H - \ddot{\omega}_{11}^E) &= 0. \end{aligned} \quad (107)$$

D. Higher-order approximations

Now we turn to the set of equations (75-78). By considering several recurrent equations, we conclude that the approximation of n th order has the form

$$\phi^{(n)} = \alpha_1^{(n)}\varphi_*^X(z) + \alpha_2^{(n)}\varphi_*^Y(z) + G^{(n)}\left(\alpha_1^{(n-1)}, \alpha_2^{(n-1)}, \dots, \alpha_1, \alpha_2\right), \quad (108)$$

where $G^{(n)}$ is the linear combination of the derivatives of the functions $\alpha_j^{(k)}$, $j = 1, 2$, $k = 1 \dots n-1$, with respect to the variables ξ, η, ζ with known coefficients. For example, in the principal order, owing to the formula (80), $G^{(0)} \equiv 0$. In the first order approximation, by (90), $G^{(1)}$ contains the derivatives of $\alpha_j^{(0)} \equiv \alpha_j$, $j = 1, 2$, up to the first order:

$$G^{(1)} \equiv -i\left(\frac{\partial\alpha_1}{\partial\xi} - \frac{\partial\alpha_2}{\partial\eta}\right)\frac{\partial\varphi_*^H}{\partial p_x} - i\left(\frac{\partial\alpha_1}{\partial\eta} + \frac{\partial\alpha_2}{\partial\xi}\right)\frac{\partial\varphi_*^E}{\partial p_x} - i\frac{\partial\alpha_1}{\partial\zeta}\frac{\partial\varphi_*^X}{\partial p_z} - i\frac{\partial\alpha_2}{\partial\zeta}\frac{\partial\varphi_*^Y}{\partial p_z}. \quad (109)$$

To find the approximation $\phi^{(2)}$ we consider the following inhomogeneous equations:

$$\mathcal{A}_*\Upsilon_j^{2H} = \Gamma_j\frac{\partial\varphi_*^H}{\partial p_x}, \quad \mathcal{A}_*\Upsilon_j^{2E} = \Gamma_j\frac{\partial\varphi_*^E}{\partial p_x}, \quad (110)$$

$$\mathcal{A}_*\Upsilon_j^{2X} = \Gamma_j\frac{\partial\varphi_*^X}{\partial p_z}, \quad \mathcal{A}_*\Upsilon_j^{2Y} = \Gamma_j\frac{\partial\varphi_*^Y}{\partial p_z}, \quad j = 1, 2, 3. \quad (111)$$

Each of these equations is a system of the form (75) with nonzero right-hand sides. It is necessary to check the solvability of these equations in the class $\mathcal{M}$. To do this, we check the conditions imposed in Lemma 2. This means that the conditions (83) must be satisfied:

$$(\varphi_*^X, \mathbf{F}) = 0, \quad (\varphi_*^Y, \mathbf{F}) = 0, \quad (112)$$

where $\mathbf{F}$ stands for each expression on the right-hand sides of the equations (110), (111). By taking all the possible combinations of the form

$$\begin{aligned} \left(\varphi_*^f, \Gamma_j \frac{\partial \varphi_*^H}{\partial p_x} \right) &= 0, & \left(\varphi_*^f, \Gamma_j \frac{\partial \varphi_*^E}{\partial p_x} \right) &= 0, \\ \left(\varphi_*^f, \Gamma_j \frac{\partial \varphi_*^X}{\partial p_z} \right) &= 0, & \left(\varphi_*^f, \Gamma_j \frac{\partial \varphi_*^Y}{\partial p_z} \right) &= 0, \quad j = 1, 2, 3, \quad f = X, Y, \end{aligned} \quad (113)$$

we obtain 24 conditions, 18 of them are satisfied (which follows from (65), (66), (68)), and 6 are not satisfied (which follows from (62), (63) and (64)). Nonhomogeneous equations from the set (110), (111), for which the solvability conditions are satisfied, have solutions in the class $\mathcal{M}$. The other equations also have solutions, which do not belong to the class $\mathcal{M}$ and are nonperiodic.

Next we take the sum of the equations for Υ_j^{2H} , Υ_j^{2E} , Υ_j^{2X} , Υ_j^{2Y} , $j = 1, 2, 3$, with coefficients such that the sum of the right-hand side expressions coincides with $F^{(2)} \equiv -i\hat{\Gamma} \cdot \nabla_{\rho} \phi^{(1)}$. The solution of the obtained sum of equations belongs to the class $\mathcal{M}$, because the conditions of solvability, which are reduced to (107), are satisfied. Thus, we get

$$\begin{aligned} G^{(2)} &\equiv -i \left(\frac{\partial \alpha_1^{(1)}}{\partial \xi} - \frac{\partial \alpha_2^{(1)}}{\partial \eta} \right) \frac{\partial \varphi_*^H}{\partial p_x} - i \left(\frac{\partial \alpha_1^{(1)}}{\partial \eta} + \frac{\partial \alpha_2^{(1)}}{\partial \xi} \right) \frac{\partial \varphi_*^E}{\partial p_x} - \\ &\quad - i \frac{\partial \alpha_1^{(1)}}{\partial \zeta} \frac{\partial \varphi_*^X}{\partial p_z} - i \frac{\partial \alpha_2^{(1)}}{\partial \zeta} \frac{\partial \varphi_*^Y}{\partial p_z} - \\ &\quad - \sum_{j=1}^3 \nabla_j \Gamma_j \left[\left(\frac{\partial \alpha_1}{\partial \xi} - \frac{\partial \alpha_2}{\partial \eta} \right) \Upsilon_j^{2H}(z) + \left(\frac{\partial \alpha_1}{\partial \eta} + \frac{\partial \alpha_2}{\partial \xi} \right) \Upsilon_j^{2E}(z) + \right. \\ &\quad \left. + \frac{\partial \alpha_1}{\partial \zeta} \Upsilon_j^{2X} + \frac{\partial \alpha_2}{\partial \zeta} \Upsilon_j^{2Y} \right], \quad \nabla_1 = \frac{\partial}{\partial \xi}, \nabla_2 = \frac{\partial}{\partial \eta}, \nabla_3 = \frac{\partial}{\partial \zeta}. \end{aligned} \quad (114)$$

In an analogous manner, we can derive that the term $G^{(3)}$ contains the first derivatives of $\alpha_1^{(2)}$ and $\alpha_2^{(2)}$, the second derivatives of $\alpha_1^{(1)}$ and $\alpha_2^{(1)}$, and the third derivatives of α_1 and α_2 . The approximation $\phi^{(k)}$ contains yet unknown functions $\alpha_j^{(k)}$, $j = 1, 2$, and $G^{(k)}$, which depends on the first derivatives of $\alpha_1^{(k-1)}$ and $\alpha_2^{(k-1)}$, the second derivatives of $\alpha_1^{(k-2)}$ and $\alpha_2^{(k-2)}$, and the derivatives of the k th order of α_1 and α_2 . The solvability conditions of $\phi^{(k+1)}$,

$$\left(\varphi_*^X, \hat{\Gamma} \cdot \nabla_{\rho} \phi^{(k)} \right) = 0, \quad \left(\varphi_*^Y, \hat{\Gamma} \cdot \nabla_{\rho} \phi^{(k)} \right) = 0, \quad (115)$$

provide equations for $\alpha_1^{(k-1)}$ and $\alpha_2^{(k-1)}$. By analogy with the section VIC, we obtain a

system of partial differential equations:

$$\begin{aligned} & \frac{\partial^2 \alpha_1^{(k-1)}}{\partial \xi^2} \ddot{\omega}_{11*}^H + \frac{\partial^2 \alpha_1^{(k-1)}}{\partial \eta^2} \ddot{\omega}_{11*}^E + \frac{\partial^2 \alpha_1^{(k-1)}}{\partial \zeta^2} \ddot{\omega}_{33*}^0 + 2 \frac{\delta \omega}{c} \alpha_1^{(k-1)} - \\ & - \frac{\partial^2 \alpha_2^{(k-1)}}{\partial \xi \partial \eta} (\ddot{\omega}_{11*}^H - \ddot{\omega}_{11*}^E) = A_1^{(k-1)} \left(\alpha_1^{(k-2)}, \alpha_2^{(k-2)}, \dots, \alpha_1, \alpha_2 \right), \end{aligned} \quad (116)$$

$$\begin{aligned} & \frac{\partial^2 \alpha_2^{(k-1)}}{\partial \xi^2} \ddot{\omega}_{11*}^E + \frac{\partial^2 \alpha_2^{(k-1)}}{\partial \eta^2} \ddot{\omega}_{11*}^H + \frac{\partial^2 \alpha_2^{(k-1)}}{\partial \zeta^2} \ddot{\omega}_{33*}^0 + 2 \frac{\delta \omega}{c} \alpha_2^{(k-1)} - \\ & - \frac{\partial^2 \alpha_1^{(k-1)}}{\partial \xi \partial \eta} (\ddot{\omega}_{11*}^H - \ddot{\omega}_{11*}^E) = A_2^{(k-1)} \left(\alpha_1^{(k-2)}, \alpha_2^{(k-2)}, \dots, \alpha_1, \alpha_2 \right), \end{aligned} \quad (117)$$

where $A_1^{(0)} = A_2^{(0)} = 0$, $A_1^{(k-1)}, A_2^{(k-1)}$ for $k > 1$ are linear combinations of derivatives of the already known functions $\alpha_j^{(l)}, j = 1, 2, l = 1, \dots, k-2$, with respect to the variables ξ, η , and ζ . This means that equations for approximations of all orders (75-78) can be solved step by step.

VII. SOLUTION OF THE EQUATIONS FOR α

We have obtained the equations (107) with constant coefficients, which describe the behavior of the envelopes of the field. Now we are going to discuss the methods of solving them. The simplest case arises if the field does not depend on one of the lateral coordinates, for example, on η . In this case, the equations for α_1 and α_2 are separated:

$$\begin{aligned} & \frac{\partial^2 \alpha_1}{\partial \xi^2} \ddot{\omega}_{11*}^H + \frac{\partial^2 \alpha_1}{\partial \zeta^2} \ddot{\omega}_{33*}^0 + 2 \frac{\delta \omega}{c} \alpha_1 = 0, \\ & \frac{\partial^2 \alpha_2}{\partial \xi^2} \ddot{\omega}_{11*}^E + \frac{\partial^2 \alpha_2}{\partial \zeta^2} \ddot{\omega}_{33*}^0 + 2 \frac{\delta \omega}{c} \alpha_2 = 0, \end{aligned} \quad (118)$$

where the coefficients are defined in (61) and are the derivatives of the dispersion functions for TM and TE type waves, calculated at stationary points. Equations (118) can be elliptic or hyperbolic ones depending on the type of a stationary point. According to the Appendix 1, we have $\ddot{\omega}_{11*}^f > 0$, $f = E, H$. Equations (118) are elliptic if $\ddot{\omega}_{33*}^0 > 0$, and hyperbolic if $\ddot{\omega}_{33*}^0 < 0$. We solve these equations by means of the Fourier method performing the Fourier transform with respect to the variable ξ . By dividing the obtained equations by the coefficient $\ddot{\omega}_{33*}^0$, we derive the following equations for the functions $\hat{\alpha}_j(p_\xi, \zeta)$:

$$\frac{\partial^2 \hat{\alpha}_j}{\partial \zeta^2} - \frac{\ddot{\omega}_{11*}^j}{\ddot{\omega}_{33*}^0} p_\xi^2 \hat{\alpha}_j + 2 \frac{\delta \omega}{c \ddot{\omega}_{33*}^0} \hat{\alpha}_j = 0, \quad j = 1, 2, \quad (119)$$

$$\ddot{\omega}_{11*}^1 \equiv \ddot{\omega}_{11*}^H, \quad \ddot{\omega}_{11*}^2 \equiv \ddot{\omega}_{11*}^E. \quad (120)$$

Solutions of (119) are determined by the integral

$$\alpha_j(\boldsymbol{\rho}) = \frac{1}{2\pi} \int_{\mathbb{R}} dp_\xi \, e^{ip_\xi \xi} \left[\hat{\alpha}_j^-(p_\xi) e^{ip_j \zeta} + \hat{\alpha}_j^+(p_\xi) e^{-ip_j \zeta} \right], \quad (121)$$

where $\boldsymbol{\rho} = (\xi, 0, \zeta)$ and

$$p_j \zeta = \sqrt{-p_\xi^2 \frac{\ddot{\omega}_{11*}^j}{\ddot{\omega}_{33*}^0} + 2 \frac{\delta\omega}{c \ddot{\omega}_{33*}^0}}. \quad (122)$$

If $\ddot{\omega}_{33*}^0 > 0$ and $0 < p_\xi^2 \ddot{\omega}_{11*}^j / \ddot{\omega}_{33*}^0 < 2\delta\omega / c \ddot{\omega}_{33*}^0$, then the integral describes the propagating waves governed by the elliptic equation. The components with such values of p_ξ that $p_\xi^2 \ddot{\omega}_{11*}^j > 2\delta\omega / c$ do not propagate. If $\ddot{\omega}_{33*}^0 < 0$, then introducing the notation σ_j^2, q^2 , we obtain

$$p_j \zeta = \sqrt{p_\xi^2 \sigma_j^2 + q^2}, \quad \sigma_j^2 = \frac{\ddot{\omega}_{11*}^j}{|\ddot{\omega}_{33*}^0|}, \quad q^2 = -2 \frac{\delta\omega}{c |\ddot{\omega}_{33*}^0|}. \quad (123)$$

If $\delta\omega > 0$, only the components with large p_ξ propagate. The equation (119) turns to a Klein-Gordon-Fock type equation.

If $\delta\omega = 0$, the equations (118) are the one-dimensional wave equations, where the variable ζ plays the role of time, and σ plays the role of the speed of wave propagation. The solutions can be found by the D'Alembert method and read

$$\alpha_j = F_j(\xi - \sigma\zeta) + G_j(\xi + \sigma\zeta), \quad (124)$$

where F_j and G_j are some functions. If the function F_j is localized for $\zeta = 0$ near $\xi = 0$, it is localized for any ζ near the line $\xi - \sigma\zeta = 0$ and propagates undistorted. This means that in the medium under consideration there is the possibility of existence of non-distorting beams, all of them having the the same angle with z axis equal to

$$\varphi^f = \pm \arctg \sqrt{\frac{\ddot{\omega}_{11*}^f}{|\ddot{\omega}_{33*}^0|}}, \quad f = H, E. \quad (125)$$

We have discussed and studied this effect numerically in¹⁰.

Now we proceed to the general case, where the field depends on both lateral coordinates ξ, η . We obtained equations (101) and (106) for the functions τ_1, τ_2 defined by (94). Let us take the derivative of the equation (101) with respect to ξ and of the equation (106) with respect to η and then calculate the difference. We obtain an equation for τ_1 . To get the

equation for τ_2 , we differentiate (101) with respect to η and equation (106) with respect to ξ and take the sum of the results. Thus, we find the equations for the functions τ_1, τ_2

$$\begin{aligned}\ddot{\omega}_{11*}^H \left(\frac{\partial^2 \tau_1}{\partial \xi^2} + \frac{\partial^2 \tau_1}{\partial \eta^2} \right) + \ddot{\omega}_{33*}^0 \frac{\partial^2 \tau_1}{\partial \zeta^2} + 2 \frac{\delta \omega}{c} \tau_1 &= 0, \\ \ddot{\omega}_{11*}^E \left(\frac{\partial^2 \tau_2}{\partial \xi^2} + \frac{\partial^2 \tau_2}{\partial \eta^2} \right) + \ddot{\omega}_{33*}^0 \frac{\partial^2 \tau_2}{\partial \zeta^2} + 2 \frac{\delta \omega}{c} \tau_2 &= 0.\end{aligned}\tag{126}$$

These equations are either hyperbolic or elliptic ones depending on the sign of $\ddot{\omega}_{33*}^0$. Their solutions obtained by the Fourier transform read

$$\tau_j(\boldsymbol{\rho}) = \frac{1}{(2\pi)^2} \int_{\mathbb{R}^2} dp_\xi dp_\eta e^{ip_\xi \xi + ip_\eta \eta} [\hat{\tau}_j^+(p_\xi, p_\eta) e^{-ip_j \zeta} + \hat{\tau}_j^-(p_\xi, p_\eta) e^{ip_j \zeta}], \tag{127}$$

where

$$p_{1\zeta} = \sqrt{-\frac{\ddot{\omega}_{11*}^H}{\ddot{\omega}_{33*}^0}(p_\xi^2 + p_\eta^2) + 2 \frac{\delta \omega}{c \ddot{\omega}_{33*}^0}}, \quad p_{2\zeta} = \sqrt{-\frac{\ddot{\omega}_{11*}^E}{\ddot{\omega}_{33*}^0}(p_\xi^2 + p_\eta^2) + 2 \frac{\delta \omega}{c \ddot{\omega}_{33*}^0}}, \tag{128}$$

and $\hat{\tau}_j^\pm(p_\xi, p_\eta)$ are such functions that the integrals (127) and the integrals, obtained by taking the derivative of (127), converge. For $\ddot{\omega}_{33*}^0 < 0$, $\delta \omega > 0$ only the components with large $p_\xi^2 + p_\eta^2$ propagate.

Now we are going to derive the equations for the original functions α_1, α_2 . We take the derivatives of two relations (94) with respect to η and ξ , respectively, and take their sum and difference. We obtain

$$\Delta \alpha_1 = \frac{\partial \tau_1}{\partial \xi} + \frac{\partial \tau_2}{\partial \eta}, \quad \Delta \alpha_2 = \frac{\partial \tau_2}{\partial \xi} - \frac{\partial \tau_1}{\partial \eta}, \quad \Delta \equiv \frac{\partial^2}{\partial \xi^2} + \frac{\partial^2}{\partial \eta^2}. \tag{129}$$

By the Fourier integral we get the following expressions for the functions α_1, α_2 :

$$\begin{aligned}\alpha_1(\boldsymbol{\rho}) &= \frac{-i}{(2\pi)^2} \int_{\mathbb{R}^2} dp_\xi dp_\eta e^{i(p_\xi \xi + p_\eta \eta)} \frac{p_\xi \hat{\tau}_1 + p_\eta \hat{\tau}_2}{p_\xi^2 + p_\eta^2}, \\ \alpha_2(\boldsymbol{\rho}) &= \frac{-i}{(2\pi)^2} \int_{\mathbb{R}^2} dp_\xi dp_\eta e^{i(p_\xi \xi + p_\eta \eta)} \frac{p_\xi \hat{\tau}_2 - p_\eta \hat{\tau}_1}{p_\xi^2 + p_\eta^2},\end{aligned}\tag{130}$$

where

$$\hat{\tau}_j \equiv \hat{\tau}_j^+(p_\xi, p_\eta) e^{-ip_j \zeta} + \hat{\tau}_j^-(p_\xi, p_\eta) e^{ip_j \zeta}. \tag{131}$$

We also require the functions $\hat{\tau}_j p_\xi / (p_\xi^2 + p_\eta^2)$ and $\hat{\tau}_j p_\eta / (p_\xi^2 + p_\eta^2)$ to be continuous and integrable.

The expressions for α_1, α_2 can also be rewritten in the polar coordinate system (p_ρ, γ) as

$$\begin{aligned}\alpha_1(\boldsymbol{\rho}) &= \frac{-i}{(2\pi)^2} \int_0^{+\infty} dp_\rho \int_0^{2\pi} d\gamma e^{i(p_\rho \xi \cos \gamma + p_\rho \eta \sin \gamma)} (\cos \gamma \hat{\tau}_1 + \sin \gamma \hat{\tau}_2), \\ \alpha_2(\boldsymbol{\rho}) &= \frac{-i}{(2\pi)^2} \int_0^{+\infty} dp_\rho \int_0^{2\pi} d\gamma e^{i(p_\rho \xi \cos \gamma + p_\rho \eta \sin \gamma)} (\cos \gamma \hat{\tau}_2 - \sin \gamma \hat{\tau}_1),\end{aligned}\tag{132}$$

where $p_\rho = \sqrt{p_\xi^2 + p_\eta^2}$, $\cos \gamma = p_\xi/p_\rho$, $\sin \gamma = p_\eta/p_\rho$.

We express also the principal approximation of the asymptotic solutions in terms of TM and TE solutions at the stationary point determined by the passage to the limit in every direction (29). Substituting solution of (107) given by (132) in formula (80), we obtain the integral representation

$$\begin{pmatrix} \mathbf{E} \\ \mathbf{H} \end{pmatrix} (z, \boldsymbol{\rho}) \simeq \frac{-i}{(2\pi)^2} \int_0^{+\infty} dp_\rho \int_0^{2\pi} d\gamma e^{i(p_\rho \xi \cos \gamma + p_\rho \eta \sin \gamma)} (\hat{\tau}_1 \boldsymbol{\Phi}_*^H(z) + \hat{\tau}_2 \boldsymbol{\Phi}_*^E(z)),\tag{133}$$

where $\boldsymbol{\Phi}_*^H(z)$ and $\boldsymbol{\Phi}_*^E(z)$ depend on the direction of propagation according to (29).

VIII. CONCLUSIONS

We have elaborated a formal asymptotic approach for monochromatic electromagnetic fields in a layered periodic structure. The frequency of the field is close to that of a stationary point $\mathbf{p}_*$ of one of the sheets of the dispersive surface $\omega = \omega^f(\mathbf{p})$. Here f stands for the type of the polarization, which may be H for TM- or E for TE- polarization. The dispersive surfaces for waves of different polarizations are distinct, but the stationary points of them coincide. For the conditions listed in Section VI, we found asymptotic series for the solutions of Maxwell equations (5) by the two-scale expansions method. The field is assumed to be a function of a fast variable z and slow variables $\boldsymbol{\rho}$; see (71). The field in the principal approximation is represented as a linear combination of Floquet-Bloch solutions of different polarizations $\boldsymbol{\Phi}_*^f(z)$, $f = X$ or Y with slowly varying envelopes $\alpha_j(\boldsymbol{\rho})$, $j = 1, 2$. It reads

$$\boldsymbol{\Psi} = \begin{pmatrix} \mathbb{E} \\ \mathbb{H} \end{pmatrix} (z, \boldsymbol{\rho}) \simeq \alpha_1(\boldsymbol{\rho}) \boldsymbol{\Phi}_*^X(z) + \alpha_2(\boldsymbol{\rho}) \boldsymbol{\Phi}_*^Y(z),\tag{134}$$

where

$$\boldsymbol{\Phi}_*^f(z) \equiv \boldsymbol{\Phi}^f(z, \mathbf{p}_*) = e^{ip_{z*}z} \boldsymbol{\varphi}_*^f, \quad f = X, Y,\tag{135}$$

where $\mathbf{p}_* = (0, 0, p_{z*})$, $p_{z*} = 0, \pm\pi/b$. The functions $\Phi^f(z, \mathbf{p})$ are Floquet-Bloch solutions of the system (15). For $\mathbf{p} = \mathbf{p}_*$, they are expressed in terms of (E_0, H_0) (see, (21)), which are Floquet-Bloch solutions of the system (18) with the quasimomentum p_{z*} .

The envelope functions α_j , $j = 1, 2$, are defined by the equations with constant coefficients (107). These coefficients are the second derivatives of the dispersion functions, i.e., the coefficients of the Taylor expansion of $\omega = \omega^f(\mathbf{p})$ near the stationary points $\mathbf{p}_* = (0, 0, p_{z*})$

$$\omega = \omega_* + \frac{1}{2}\ddot{\omega}_{11*}^f(p_x^2 + p_y^2) + \frac{1}{2}\ddot{\omega}_{33*}^0(p_z - p_{z*})^2 + \dots, \quad (136)$$

where $\ddot{\omega}_{11*}^f$, $\ddot{\omega}_{33*}^0$ are the second derivatives of the dispersion function ω with respect to p_x and p_z calculated at the stationary point. Since the problem is axially symmetric, the derivatives of the dispersion functions with respect to p_x and p_y are equal and depend on the type of the polarization, while the derivatives with respect to p_z do not depend on the type of the polarization.

The system (107) can be split by introducing new functions τ_j , $j = 1, 2$, by means of (94). As was obtained in Section VII, the functions τ_1 and τ_2 satisfy the equations (126). The coefficients α_j , $j = 1, 2$, are expressed in terms of both τ_j , $j = 1, 2$, in (132). The system can be split into two separated equations only if the field does not depend on one of the spatial coordinates. Such analysis was absent in the papers of Longhi^{7, 8}.

An interesting particular case arises if $\ddot{\omega}_{33*}^0 < 0$. Then the equations for τ_1 and τ_2 are hyperbolic of the Klein-Gordon-Fock type. The coordinate ζ stands for time. If additionally $\delta\omega = 0$, there are wave equations. The effects that arise if the field depends only on one lateral coordinate were studied both analytically and numerically in our paper¹⁰.

The investigation of qualitative consequences of the obtained results in the case of two lateral coordinates are out of scope of the present paper and will be discussed in the next publications. We expect that, by choosing the localized solutions of envelopes, we can construct beam-like solutions of the Maxwell equations. The obtained formulas enable us also to find a change of polarization of the field in passing through the layered periodic structure.

The results may be generalized to another equations, which can be written in matrix form (5).

APPENDIX 1

The dispersion relation

To make the paper self-contained, we obtain the dispersion relation and find stationary points of the dispersive surfaces. To do this, we consider the Floquet-Bloch solutions of the first subsystems (17):

$$\begin{pmatrix} E_{\parallel} \\ H_{\perp} \end{pmatrix} = e^{ipz} \begin{pmatrix} U_1 \\ U_2 \end{pmatrix}, \quad (137)$$

where U_1, U_2 are the periodic functions of z with period b .

We accomplish the first of subsystems (17) with the initial data $E_{\parallel} = 1, H_{\perp} = 0$ and denote the solution of such a Cauchy problem by e_1, h_1 . We introduce another solution e_2, h_2 , which satisfies (17) and the initial data $E_{\parallel} = 0, H_{\perp} = 1$. Both solutions are smooth in the intervals, where ε, μ are continuous, and continuous at the points of discontinuity of the parameters ε, μ , but, generally speaking, they are not periodic. These solutions depend on $p_{\parallel}^2, \omega$, because the coefficients of (17) depend on these parameters. These solutions are linear independent and form a basis in the space of the solutions of the first subsystem of (17). We introduce the matrix $\mathbf{M}$ of the solutions $(e_1, h_1)^t$ and $(e_2, h_2)^t$ as follows:

$$\mathbf{M}(z; p_{\parallel}^2, \omega) = \begin{pmatrix} e_1 & e_2 \\ h_1 & h_2 \end{pmatrix} (z; p_{\parallel}^2, \omega). \quad (138)$$

The matrix $\mathbf{M}(b; p_{\parallel}^2, \omega)$ is then a monodromy matrix:

$$\mathbf{M}(z + b; p_{\parallel}^2, \omega) = \mathbf{M}(z; p_{\parallel}^2, \omega) \mathbf{M}(b; p_{\parallel}^2, \omega). \quad (139)$$

We seek the Floquet-Bloch solutions in the following form:

$$\begin{pmatrix} E_{\parallel} \\ H_{\perp} \end{pmatrix} = \mathbf{M}(z; p_{\parallel}^2, \omega) \begin{pmatrix} \beta_1 \\ \beta_2 \end{pmatrix}, \quad (140)$$

where $(\beta_1, \beta_2)^t$ is the eigenvector corresponding to the eigenvalue λ of the problem:

$$(\mathbf{M}(b; p_{\parallel}^2, \omega) - \lambda \mathbf{I}) \begin{pmatrix} \beta_1 \\ \beta_2 \end{pmatrix} = \begin{pmatrix} 0 \\ 0 \end{pmatrix}, \quad (141)$$

here $\mathbf{I}$ is the identity matrix. The equation for λ is expressed in terms of the determinant and the trace of the matrix $\mathbf{M}$. The determinant of the matrix $\mathbf{M}(b; p_{\parallel}^2, \omega)$ is the Wronskian

of the solutions $(e_1, h_1)^t$ and $(e_2, h_2)^t$ of the system (17) at $z = b$. It is constant by the Ostrogradskiy-Liouville theorem and, thus, can be calculated for any z . For $z = 0$ it is equal to 1, so $\det \mathbf{M}(b; p_{\parallel}^2, \omega) = 1$ and λ satisfies the quadratic equation

$$\lambda^2 + \text{Sp} \mathbf{M}(b; p_{\parallel}^2, \omega) \lambda + 1 = 0. \quad (142)$$

In order to obtain the Floquet-Bloch solutions, we require $|\lambda| = 1$ and we may assume $\lambda_1 = e^{ip_z b}$, where p_z is real-valued. Then $\lambda_2 = e^{-ip_z b}$ and

$$M_{11}(b; p_{\parallel}^2, \omega) + M_{22}(b; p_{\parallel}^2, \omega) = 2 \cos(p_z b). \quad (143)$$

This equation establishes the relation between p_z , $p_{\parallel}^2$ and ω , so we consider below only two of these three variables as free parameters. We denote $\mathcal{F} \equiv M_{11}(b; p_{\parallel}^2, \omega) + M_{22}(b; p_{\parallel}^2, \omega)$. The function $\mathcal{F} \equiv \mathcal{F}(p_{\parallel}^2, \omega)$ depends on the problem parameters $\omega, p_{\parallel}$ analytically, because the coefficients of the system (17) depend on these parameters analytically if $\omega \neq 0$. Therefore the dispersion relation (143) can be written in the form of

$$\mathcal{F}(p_{\parallel}^2, \omega) - \cos(p_z b) = 0. \quad (144)$$

The function $\mathcal{F}$ is an oscillating real-valued function of ω , its minima and maxima are larger than or equal 1 (see, for example,¹⁸). The corresponding p_z changes from $-\pi/b$ to π/b . If $|\mathcal{F}|$ is greater than 1 for some interval of ω , then the bounded solutions do not exist and such interval is called the forbidden zone. For each interval of ω (the allowed zone), where $|\mathcal{F}| \leq 1$ and the function $\mathcal{F}$ of ω is monotone, there exists an inverse function

$$\omega = \omega_j^H(\mathbf{p}). \quad (145)$$

If $|\mathcal{F}| = 1$ and $\partial \mathcal{F} / \partial \omega = 0$, two intervals of monotone behavior of $\mathcal{F}$ touch each other at this point. Further, we assume that $\partial \mathcal{F} / \partial \omega \neq 0$. This follows from the assumption that the system has one bounded and one unbounded solutions on the boundary of the interval of the monotone behavior of $\mathcal{F}$; see, for example,¹⁸.

Analogous considerations for the second subsystem of (17) yield the dispersion relation $\omega = \omega_j^E(\mathbf{p})$ for the wave of the TE polarization.

In other words, the problem under consideration can be treated as a spectral problem for the operator

$$(-i \mathbf{P}^{-1} \mathbf{\Gamma} \cdot \nabla + \mathbf{P}^{-1}(\mathbf{p} \cdot \mathbf{\Gamma})) \boldsymbol{\varphi} = \frac{\omega}{c_0} \boldsymbol{\varphi}, \quad \boldsymbol{\varphi} \in \mathcal{M}, \quad (146)$$

where ω plays the role of the spectral parameter and $\mathbf{p}$ is an external parameter of the problem. For fixed $\mathbf{p}$, the operator has a discrete set of eigenvalues $\omega = \omega_j$. For $\mathbf{p} \in \mathbb{R}^2 \times (-\pi/b, \pi/b)$, $\omega_j(\mathbf{p})$ forms a sheet of number j .

The stationary points of the dispersive surface

We are going to find at least one stationary point of a single-valued function ω_j^H , where j is the number of the sheet of the dispersive surface. Below we omit j for the sake of brevity. We consider only such zones, where $\partial\mathcal{F}/\partial\omega \neq 0$ on the entire zone. We take the derivative of the implicitly defined function

$$\frac{\partial\omega^H}{\partial p_{\parallel}} = -2p_{\parallel} \frac{\partial\mathcal{F}}{\partial(p_{\parallel}^2)} \bigg/ \frac{\partial\mathcal{F}}{\partial\omega}, \quad \frac{\partial\omega^H}{\partial p_z} = -b \sin p_z b \bigg/ \frac{\partial\mathcal{F}}{\partial\omega}. \quad (147)$$

We note that $\partial\omega^H/\partial p_z$ vanishes for $p_z = 0, \pm\pi/b$. The function $\omega^H(\mathbf{p})$ is a periodic function of p_z with period $2\pi/b$. The derivative $\partial\omega^H/\partial p_{\parallel}$ vanishes at least at the point $p_{\parallel} = 0$ since $\mathcal{F}$ depends on $p_{\parallel}^2$. We denote the stationary points with asterisk subscript: $\omega_* = \omega^H(\mathbf{p}_*)$, $p_{x*} = p_{y*} = 0$, $p_{z*} = 0, \pm\pi/b$. We note that such stationary points are the bounds of the forbidden zones since $\cos p_{z*}b = \pm 1$, and hence $\mathcal{F} = \pm 1$.

Now we consider the second derivatives of ω . First, we find the second derivative with respect to p_z from the formula (147). At a stationary point it reads

$$\frac{\partial^2\omega^H}{\partial p_z^2} = -b^2 \cos p_{z*}b \bigg/ \frac{\partial\mathcal{F}}{\partial\omega} - b \sin p_{z*}b \frac{\partial}{\partial p_z} \left(\frac{\partial\mathcal{F}}{\partial\omega} \right). \quad (148)$$

The second term is equal to zero owing to (144), and the first term has a constant nonzero numerator and a denominator with the sign changing on each sheet of the function ω . Now we consider the second derivative of ω with respect to p_x (or p_y). By (62), we get

$$\frac{\ddot{\omega}_{11*}^H}{c} u_*^{XX} = 2 \left(\varphi_*^X, \Gamma_1 \frac{\partial\varphi_*^H}{\partial p_x} \right), \quad (149)$$

where

$$\frac{\partial^2\omega^H}{\partial p_x^2} \bigg|_{\mathbf{p}_*} \equiv \ddot{\omega}_{11*}^H. \quad (150)$$

By the formula (31) and the definition of the matrix (7), we conclude that the scalar product on the right-hand side of the formula (149) is equal to the integral of $|H_0|^2/(k\varepsilon)$ with respect to z and hence it is positive if $\varepsilon > 0$. Since $u^{XX} > 0$ for $\varepsilon > 0, \mu > 0$, the second derivative $\ddot{\omega}_{11*}^H > 0$. This means that the stationary points of ω are of two different types: hyperbolic and elliptic, depending on the sign of the second derivative with respect to p_z .

The Floquet-Bloch amplitudes

We seek the Floquet-Bloch solutions in the form (140), where $(\beta_1, \beta_2)^t$ is the eigenvector of the monodromy matrix (141), which corresponds to the eigenvalue λ . Up to an arbitrary constant factor, $\beta_1 = M_{12}, \beta_2 = M_{11} - \lambda_1$. We denote the variable U corresponding to the choice of the sign $\pm$ in the exponent $e^{\pm ip_z b}$ with a subscript $\pm$. We consider TM-type solution and denote it by the superscript H . Thus,

$$\mathbf{U}_+^H = e^{-ip_z z} \left(M_{12} \begin{pmatrix} e_1 \\ h_1 \end{pmatrix} + (M_{11} - \lambda_1) \begin{pmatrix} e_2 \\ h_2 \end{pmatrix} \right). \quad (151)$$

Here $(e_j, h_j)^t, j = 1, 2$ depends on the variable z and on the parameters $p_{\parallel}^2, \omega$. The monodromy matrix also depends on $p_{\parallel}^2, \omega$. We assume that the Floquet-Bloch solutions are expressed in terms of $\mathbf{p}$. We note that $p_{\parallel}^2 = p_x^2 + p_y^2$ and take into account the dispersion relation (145). The formula (137) takes a form:

$$\begin{pmatrix} E_{\parallel} \\ H_{\perp} \end{pmatrix} (z; \mathbf{p}) = e^{ip_z z} \mathbf{U}_+^H(z; p_z, p_{\parallel}^2, \omega^H(\mathbf{p})), \quad \mathbf{U}_+^H = \begin{pmatrix} U_1 \\ U_2 \end{pmatrix}. \quad (152)$$

The second Floquet-Bloch solution is obtained by replacing p_z by $-p_z$, and $\mathbf{U}_+^H$ by $\mathbf{U}_-^H$.

An exception is the case $p_z = p_{z*}, p_{z*} = 0, \pm\pi/b$. Each point p_{z*} corresponds to the boundary of the forbidden zone, where $|\mathcal{F}(p_{\parallel}^2, \omega)| = 1$. Then the double root of the dispersion equation (142) is $\lambda_1 = \lambda_2 = \pm 1$. We assume that $M_{12} \neq 0$. Formulas (152), (151) determine the unique, up to the constant factor, solution for $\mathbf{p} = \mathbf{p}_*$ (i.e., $p_{\parallel} = p_{\parallel*} = 0, p_z = p_{z*}$). We seek the second linearly independent solution in the form of

$$\begin{pmatrix} E_{\parallel 2} \\ H_{\perp 2} \end{pmatrix} (z; \mathbf{p}_*) = \mathbf{M}(z; 0, \omega_*) \begin{pmatrix} \gamma_1 \\ \gamma_2 \end{pmatrix}, \quad (153)$$

where the coefficients are found from the equation

$$(\mathbf{M}(b; 0, \omega_*) - \lambda \mathbf{I}) \begin{pmatrix} \gamma_1 \\ \gamma_2 \end{pmatrix} = \begin{pmatrix} \beta_1 \\ \beta_2 \end{pmatrix}. \quad (154)$$

Then the solution (153) satisfies the relation

$$\begin{pmatrix} E_{\parallel 2} \\ H_{\perp 2} \end{pmatrix} (z + b; \mathbf{p}_*) = \lambda \begin{pmatrix} E_{\parallel 2} \\ H_{\perp 2} \end{pmatrix} (z; \mathbf{p}_*) + \begin{pmatrix} E_{\parallel} \\ H_{\perp} \end{pmatrix} (z; \mathbf{p}_*), \quad (155)$$

and can be written as

$$\begin{pmatrix} E_{\parallel 2}(z; \mathbf{p}_*) \\ H_{\perp 2}(z; \mathbf{p}_*) \end{pmatrix} = e^{ip_{z*}z} \left[\frac{z}{\lambda b} \mathbf{U}_+^H(z; p_{z*}, 0, \omega_*) + \mathbf{Q}^H(z; p_{z*}, \omega_*) \right], \quad (156)$$

where $\mathbf{U}_+^H$, $\mathbf{Q}^H$ are periodic functions of the variable z , the function $\mathbf{U}_+^H$ is defined by (151). We note that $\mathbf{U}_+^H$ and $\mathbf{U}_-^H$ are proportional at the point $\mathbf{p}_*$.

For waves of the TE polarization, the Floquet-Bloch amplitudes are obtained analogously.

APPENDIX 2

Let $\mathcal{M}$ be a class of six-component vector-valued functions of z , which are periodic with period b , piecewise smooth on the period, and their components with numbers 1, 2, 4, 5 are continuous.

(A piecewise function is a function that can be broken into a finite number of distinct pieces and on each piece both the function and its derivative are continuous, even though the whole function may have a jump discontinuity at points between the pieces.)

Lemma 1.

The operator $\mathcal{A}_*$ defined by (41) and (45) on the class of functions $\mathcal{M}$ is symmetric, i.e., for any $\mathbf{w}, \mathbf{v} \in \mathcal{M}$ the following relation is valid:

$$(\mathbf{v}, \mathcal{A}_* \mathbf{w}) = (\mathcal{A}_* \mathbf{v}, \mathbf{w}). \quad (157)$$

This fact follows from the definition of the operator $\mathcal{A}_*$. Since $\mathbf{P}$ is a real-valued matrix and $\mathbf{v}, \mathbf{w} \in \mathcal{M}$, we derive by integration by parts that

$$(\mathbf{v}, \mathcal{A}_* \mathbf{w}) = \left(\mathbf{v}, k_* \mathbf{P} \mathbf{w} + i \Gamma_3 \frac{\partial \mathbf{w}}{\partial z} - p_{z*} \Gamma_3 \mathbf{w} \right) = (\mathcal{A}_* \mathbf{v}, \mathbf{w}) + i \sum_{m=0}^M [\langle \mathbf{v}, \Gamma_3 \mathbf{w} \rangle]_m, \quad (158)$$

where $\langle \cdot, \cdot \rangle$ is a scalar product dependent on z ; see (8). By the definition of Γ_3 , see (7), we get

$$\langle \mathbf{v}(z), \Gamma_3 \mathbf{w}(z) \rangle = \overline{v_1(z)} w_5(z) - \overline{v_2(z)} w_4(z) - \overline{v_4(z)} w_2(z) + \overline{v_5(z)} w_1(z). \quad (159)$$

We denote a jump of any scalar function $h(z)$ at the point z_m by

$$[h]_m = h(z_m + 0) - h(z_m - 0), \quad m \neq 0; \quad [h]_0 = h(b) - h(0). \quad (160)$$

The summation over all discontinuities of $\mathbf{v}$ and $\mathbf{w}$ is implied in (158). Since $\mathbf{v}, \mathbf{w} \in \mathcal{M}$, the function $\langle \mathbf{v}(z), \mathbf{\Gamma}_3 \mathbf{w}(z) \rangle$ is continuous, the terms outside the integral in (158) vanish, and the symmetry of $\mathcal{A}_*$ is proved.

Now we proceed to the proof of **Lemma 2**, which states that a solution from the class $\mathcal{M}$ of the equation

$$\mathcal{A}_* \phi = \mathbf{F} \quad (161)$$

exists if and only if the following conditions are satisfied:

$$(\varphi_*^X, \mathbf{F}) = 0, \quad (\varphi_*^Y, \mathbf{F}) = 0, \quad (162)$$

where the operator $\mathcal{A}_*$ is defined by the formula (76), the functions $\varphi_*^X(z)$, $\varphi_*^Y(z)$ are defined by (48), (33), and (21) and belong to $\mathcal{M}$.

In order to prove the lemma, we take the scalar product of (161) and φ_*^X :

$$(\varphi_*^X, \mathcal{A}_* \phi) = (\varphi_*^X, \mathbf{F}). \quad (163)$$

First, if a solution of (161) $\phi \in \mathcal{M}$, then the scalar product, by the symmetry of $\mathcal{A}_*$, can be rewritten as $(\varphi_*^X, \mathcal{A}_* \phi) = (\mathcal{A}_* \varphi_*^X, \phi)$, and since $\mathcal{A}_* \varphi_*^X = 0$, it follows that the scalar product on the right-hand side of the equation (163) is also equal to zero.

Now let $(\varphi_*^X, \mathbf{F}) = 0$. The equation (161) for the vector-valued function $\phi = (\phi_1, \phi_2, \phi_3, \phi_4, \phi_5, \phi_6)^T$ has the form

$$\begin{cases} k\varepsilon\phi_1 + i\frac{\partial\phi_5}{\partial z} - p_{z*}\phi_5 = F_1 \\ k\mu\phi_5 + i\frac{\partial\phi_1}{\partial z} - p_{z*}\phi_1 = F_5 \\ k\varepsilon\phi_3 = F_3 \end{cases} \quad \begin{cases} k\mu\phi_4 - i\frac{\partial\phi_2}{\partial z} + p_{z*}\phi_2 = F_4 \\ k\varepsilon\phi_2 - i\frac{\partial\phi_4}{\partial z} + p_{z*}\phi_4 = F_2 \\ k\mu\phi_6 = F_6. \end{cases} \quad (164)$$

It splits into the pair of nonhomogeneous systems by the components with numbers 1,5 and 2,4, respectively. The components with numbers 3 and 6 are found explicitly. We consider one of the subsystems for the components 1,5, and the second system is considered similarly. The solution of the subsystem can always be represented as a sum

$$\begin{pmatrix} \phi_1 \\ \phi_5 \end{pmatrix} = A \mathbf{U}_+^H(z; p_{z*}, 0, \omega_*) + B \left[\frac{z}{b\lambda} \mathbf{U}_+^H(z; p_{z*}, 0, \omega_*) + \mathbf{Q}^H(z; p_{z*}, \omega_*) \right] + \begin{pmatrix} \tilde{\phi}_1 \\ \tilde{\phi}_5 \end{pmatrix},$$

where the first two terms are the Floquet-Bloch amplitudes satisfying the homogeneous system, A, B are some coefficients dependent on slow variables as on parameters, and $(\tilde{\phi}_1, \tilde{\phi}_5)^t$ indicates the particular vector solution of the nonhomogeneous equation, which in general does not belong to the class $\mathcal{M}$. We show now that this solution can be chosen continuous at all the points inside $(0, b)$. To get the continuity inside $(0, b)$, we note that the solution $(\tilde{\phi}_1, \tilde{\phi}_5)^t$ is always smooth on the intervals, where the parameters ε, μ are continuous. It can have jumps at the boundary points of these intervals. At boundary points inside the period $(0, b)$, the jumps can be compensated by addition of the solutions of homogeneous equation with appropriate coefficients, which depend on intervals. However, at the end of the period, the solution $(\tilde{\phi}_1, \tilde{\phi}_5)^t$ may differ from the value at the beginning of the period with jump $([\tilde{\phi}_1]_0, [\tilde{\phi}_5]_0)^t$; see (160) for explanation of the notation. Integrating by parts, we obtain the following expression:

$$\begin{aligned} (\varphi_*^X \mathcal{A}_* \phi) &= (\mathcal{A}_* \varphi_*^X, \phi) + \overline{E_0(0; \mathbf{p}_*)} [\phi_5]_0 + \overline{H_0(0; \mathbf{p}_*)} [\phi_1]_0 \\ &= \overline{E_0(0; \mathbf{p}_*)} [\phi_5]_0 + \overline{H_0(0; \mathbf{p}_*)} [\phi_1]_0 = (\varphi_*^X, \mathbf{F}) = 0, \end{aligned} \quad (165)$$

where

$$\begin{pmatrix} [\phi_1]_0 \\ [\phi_5]_0 \end{pmatrix} = \frac{1}{\lambda} B \mathbf{U}_+^H(b; p_{z*}, 0, \omega_*) + \begin{pmatrix} [\tilde{\phi}_1]_0 \\ [\tilde{\phi}_5]_0 \end{pmatrix}. \quad (166)$$

The jump of one of the components $\tilde{\phi}_1$ or $\tilde{\phi}_5$ of the particular solution at the end of the period can always be compensated by an appropriate choice of the coefficient B of the nonperiodic solution of the homogeneous equation. The jump of the other component vanishes by (165) if $H_0(0; \mathbf{p}_*) \neq 0$, $E_0(0; \mathbf{p}_*) \neq 0$. Then the constructed solution to the problem $\mathcal{A}_* \phi = \mathbf{F}$ belongs to the class $\mathcal{M}$ and the lemma is proved. If $E_0(0; \mathbf{p}_*)$ or $H_0(0; \mathbf{p}_*)$ is equal to zero, we take the beginning of the period at another point.

ACKNOWLEDGEMENTS

This work was supported by RFBR grant 140200624 (M.V.P. and M.S.S.) and by SPbGU grant 11.38.263.2014 (M.V.P.).

REFERENCES

- ¹J. D. Joannopoulos, S. G. Johnson, J. N. Winn, and R. D. Meade, *Photonic Crystals. Molding the Flow of Light* (Princeton University Press, Princeton, 2008).
- ²N. S. Bahvalov and G. P. Panasenko, *Averaging methods for processes in periodic bodies (in russian)* (Moscow, Nauka, 1984).
- ³V. V. Jikov, S. M. Kozlov, and O. A. Oleinik, *Homogenization of differential operators and integral functionals* (Springer, Berlin, 1994) translated from russian Homogenization of differential operators, Nauka, Moscow 1993.
- ⁴E. Sanchez-Palencia, *Non-Homogeneous Media and Vibration Theory*, Lecture Notes in Physics, Vol. 127 (Springer-Verlag, 1980).
- ⁵A. Poddubny, I. Iorsh, P. Belov, and Y. Kivshar, “Hyperbolic metamaterials,” *Nature Photonics* **7**, 948–957 (2013).
- ⁶P. Belov and Y. Hao, “Subwavelength imaging at optical frequencies using a transmission device formed by a periodic layered metal-dielectric structure operating in the canalization regime,” *Phys. Rev. B* **73**, 113110 (2006).
- ⁷S. Longhi, “Localized and nonspreading spatiotemporal wannier wave packets in photonic crystals,” *Phys. Rev. E* **71**, 016603 (2005).
- ⁸S. Longhi and D. Janner, “Localization and wannier wave packets in photonic crystals without defects,” in *Localized Waves*, edited by H. E. Hernandez-Figueroa, M. Zamboni-Rached, and E. Recami (John Wiley & Sons, Inc, 2008) pp. 315–337.
- ⁹*Localized Waves* (John Wiley & Sons, Inc, 2008) eds. H. E. Hernandez-Figueroa and M. Zamboni-Rached and E. Recami.
- ¹⁰M. S. Sidorenko and M. V. Perel, “Analytic approach to the directed diffraction in a one-dimensional photonic crystal slab,” *Phys. Rev. B* **86**, 035119 (2012).
- ¹¹H.-T. Chien, H.-T. Tang, C.-H. Kuo, C.-C. Chen, and Z. Ye, “Directed diffraction without negative refraction,” *Phys. Rev. B* **70**, 113101 (2004).
- ¹²L. B. Felsen and N. Marcuvitz, *Radiation and Scattering of Waves* (Wiley-IEEE Press, 2001).
- ¹³M. V. Perel’, “Overexcitation of modes in an anisotropic earth-ionosphere waveguide on transequatorial paths in the presence of two close degeneracy points,” *Radiophysics and Quantum Electronics* **33(11)**, 882–889 (1990), translated from *Izvestiya Vysshikh Ucheb-*

- nykh Zavedenii, Radiofizika, Vol. 33, No. 11, pp. 1208-1216, 1990.
- ¹⁴M. V. Perel', I. V. Fialkovskii, and A. P. Kiselev, "Resonance interaction of bending and shear modes in a non-uniform timoshenko beam," *Journal of Mathematical Sciences (New York)* **111:5**, 3775–3790 (2002), translated from *Zap. Nauchn. Sem. POMI*, 2000, Volume 264, Pages 258-284.
- ¹⁵M. V. Perel, J. D. Kaplunov, and G. A. Rogerson, "An asymptotic theory for internal reflection in weakly inhomogeneous elastic waveguides," *Wave Motion* **41(2)**, 95–108 (2005).
- ¹⁶I. V. Andronov, D. Y. Zaika, and M. V. Perel, "An effect of excitation of a transverse magnetic creeping wave when a transverse electric wave crosses the line of the coincidence of propagation constants," *Journal of Communications Technology and Electronics* **56(7)**, 798–804 (2011).
- ¹⁷I. Fialkovsky and M. Perel, "A unifying asymptotic approach for nonadiabatic transitions near pairs of real or complex turning points," *arXiv preprint arXiv:1604.07366* (2016).
- ¹⁸M. Eastham, *The spectral theory of periodic differential operators* (Scottish Academic Press, Edinburgh, 1973).